



Cisco Emergency Responder 10.5(1) Command Line Interface Guide

First Published: December 11, 2014

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The following information is for FCC compliance of Class A devices: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio-frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case users will be required to correct the interference at their own expense.

The following information is for FCC compliance of Class B devices: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment causes interference to radio or television reception, which can be determined by turning the equipment off and on, users are encouraged to try to correct the interference by using one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Modifications to this product not authorized by Cisco could void the FCC approval and negate your authority to operate the product

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <http://www.cisco.com/go/trademarks>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2014 Cisco Systems, Inc. All rights reserved.



CONTENTS

CHAPTER 1

CLI Basics 1

- CLI Overview 1
- Start CLI Session 1
- Command Completion 2
- Obtain Command Help 3
- End CLI Session 3
- Unsupported VMware Commands 4

CHAPTER 2

CLI Commands 5

- Delete Commands 5
 - delete account 5
 - delete dns 6
 - delete dscp 6
 - delete ipsec 7
 - delete process 7
 - delete smtp 8
- File Commands 8
 - file check 8
 - file delete 9
 - file dump 10
 - file get 11
 - file list 12
 - file search 13
 - file tail 14
 - file view 15
- Run and Set commands 16
 - run sql 16
 - set account 16

set account enable	17
show accountlocking	18
set accountlocking disable	18
set accountlocking enable	18
set accountlocking unlocktime	19
set cert delete	19
set cert import	20
set cert regen	20
set cli pagination	21
set cli session timeout	22
set commandcount	22
set csr gen	23
set date	23
set dscp	24
set dscp defaults	25
set dscp marking	25
set ipsec	26
set logging	26
set network cluster publisher hostname	27
set network cluster publisher ip	27
set network dhcp	28
set network dns	29
set network dns options	29
set network domain	30
set network failover	30
set network gateway	31
set network hostname	31
set network ip	33
set network max_ip_contrack	34
set network mtu	34
set network nic	35
set network ntp option	36
set network pmtud	36
set network restore	37
set network status	37

set password	38
set password age minimum	39
set password age maximum	39
set password complexity character disable	40
set password complexity character enable	40
set password complexity minimum-length	41
set password expiry maximum-age	41
set password expiry minimum-age enable	42
set password expiry minimum-age disable	42
set password expiry user maximum-age disable	42
set password expiry user maximum-age enable	43
set password expiry user minimum-age disable	43
set password expiry minimum-age enable	43
set password history	44
set password inactivity disable	44
set password inactivity enable	44
set password inactivity period	44
set password user admin	45
set password user security	45
set session maxlimit	46
set smtp	46
set timezone	47
set trace	47
set web-security	48
set webapp session timeout	49
set workingdir	50
Show Commands	50
show account	50
show cert	51
show cli pagination	51
show cli session timeout	52
show csr list	52
show ctl	53
show date	53
show diskusage	53

show dscp all	54
show dscp defaults	54
show dscp marking	55
show dscp status	55
show environment	56
show hardware	56
show ipsec	57
show logins	58
show memory	58
show myself	59
show network	59
show network cluster	61
show network ipprefs	61
set network ntp option	62
show open	62
show packages	63
show password expiry maximum-age	64
show password expiry minimum-age	64
show password expiry user maximum-age	64
show password expiry user minimum-age	64
show password history	64
show password inactivity	65
show process	65
show session maxlimit	67
show smtp	67
show stats io	68
show status	68
show tech all	69
show tech database	69
show tech database dump	70
show tech dbintegrity	70
show tech dbinuse	70
show tech dbschema	71
show tech dbstateinfo	71
show tech network	71

show tech prefs	72
show tech runtime	73
show tech systables	73
show tech system	74
show tech table	74
show tech version	75
show timezone	75
show trace	76
show ups status	77
show version	77
show webapp session timeout	77
show web-security	78
show workingdir	78
Unset Commands	78
unset ipsec	78
unset network	79
unset network domain	80
Utils Commands	80
utils auditd	80
utils core list	81
utils core analyze	81
utils create report	81
utils create report database	82
utils dbreplication dropadmindb	82
utils dbreplication status	83
utils dbreplication stop	83
utils dbreplication repair	84
utils dbreplication reset	84
utils diagnose	84
utils diagnose test	85
utils disaster_recovery backup network	85
utils disaster_recovery cancel_backup	86
utils disaster_recovery device add network	86
utils disaster_recovery device delete	87
utils disaster_recovery device list	87

utils disaster_recovery estimate_tar_size	88
utils disaster_recovery history	88
utils disaster_recovery jschLogs	88
utils disaster_recovery schedule add	89
utils disaster_recovery schedule delete	89
utils disaster_recovery schedule disable	90
utils disaster_recovery schedule enable	90
utils disaster_recovery schedule list	91
utils disaster_recovery restore network	91
utils disaster_recovery show_backupfiles tape	92
utils disaster_recovery show_backupfiles network	92
utils disaster_recovery show_registration	93
utils disaster_recovery status	93
utils fior	94
utils firewall	96
utils firewall ipv4	97
utils firewall ipv4 debug	97
utils firewall ipv4 list	98
utils firewall ipv4 status	98
utils import config	99
utils iostat	99
utils iothrottle enable	99
utils iothrottle disable	100
utils iothrottle status	100
utils network arp	100
utils network capture eth0	101
utils network connectivity	102
utils network connectivity output	102
utils network host	102
utils network ping	103
utils network traceroute	104
utils ntp	104
utils ntp restart	104
utils ntp server add	105
utils ntp server delete	106

utils ntp server list	108
utils ntp start	109
utils os kerneldump	109
utils os kerneldump ssh	110
utils os secure	110
utils remote_account	111
utils reset_application_ui_administrator_name	112
utils reset_application_ui_administrator_password	112
utils service	112
utils service list	113
utils snmp	114
utils snmp config 1/2c community-string	115
utils snmp config 3 user	115
utils snmp config mib2	116
utils snmp walk 3	117
utils snmp get 3	118
utils system	118
utils system boot	119
utils system upgrade	119
utils vmtools status	120
utils vmtools upgrade	120



CLI Basics

- [CLI Overview](#) , page 1
- [Start CLI Session](#) , page 1
- [Command Completion](#), page 2
- [Obtain Command Help](#) , page 3
- [End CLI Session](#) , page 3
- [Unsupported VMware Commands](#) , page 4

CLI Overview

This guide describes Cisco Unified Operating System (OS) commands that you can use on the Cisco Emergency Responder (Emergency Responder) platform to perform basic operating system functions. The Cisco Unified OS Administration web interface also makes these functions available. Typically, you would use the CLI only when a problem occurs while you are using the Cisco Unified OS Administration web interface.



Note

The File I/O Reporting Service (FIOR) provides a kernel-based daemon for collecting file I/O per process. It must be enabled from the CLI; it is disabled by default.

Start CLI Session

You can access the CLI remotely or locally using the following methods:

- You can access the CLI remotely from a web client workstation, such as the workstation that you use for Emergency Responder administration, by using secure shell (SSH) to connect securely to the Emergency Responder.
- You can access the CLI locally by using the monitor and keyboard that you used during installation or by using a terminal server that is connected to the serial port. Use this method if a problem exists with the IP address.

Before You Begin

Ensure that you have the following information, which is defined during installation:

- A primary IP address and hostname
- An administrator ID
- An administrator password

You need this information to log in to the Emergency Responder platform.

Procedure

Step 1 Depending on your method of access, do one of the following actions:

- From a remote system, use SSH to connect securely to the Emergency Responder platform. In your SSH client, enter:

```
ssh adminname@hostname
```

adminnam specifies the administrator ID and *hostname* specifies the hostname that was defined during installation.

For example, **ssh admin@cer-1**

- From a direct connection, you receive this prompt automatically:

cer-1 login:

cer-1 represents the host name of the system.

Enter the administrator ID that was defined during installation.

Step 2 Enter the password that was defined at installation.

The CLI prompt appears. The prompt represents the administrator ID; for example:

admin:

You can now use any CLI command.

Command Completion

To complete commands, use **Tab**:

- Enter the start of a command and press **Tab** to complete the command. For example, if you enter **se** and press **Tab**, **se** is expanded to the **set** command.
- Enter a full command name and press **Tab** to display all the commands or subcommands that are available. For example, if you enter **set** and press **Tab**, you see all of the **set** subcommands. An asterisk (*) identifies the commands that have subcommands.
- Press **Tab** to continue. The current command line repeats; no additional expansion is available.

Obtain Command Help

You can obtain two kinds of help on any command:

- Detailed help that includes a definition of the command and an example of its use
- Short query help that includes only command syntax

Procedure

- Step 1** To get detailed help, at the CLI prompt enter the **help** command which specifies the command name or the command and parameter.

Example:

```
admin:help file list activelog
activelog help:
This will list active logging files
```

```
options are:
page - pause output
detail - show detailed listing
reverse - reverse sort order
date - sort by date
size - sort by size
```

file-spec can contain '*' as wildcards

```
Example:
admin:file list activelog platform detail
02 Dec,2004 12:00:59 <dir> drf
02 Dec,2004 12:00:59 <dir> log
16 Nov,2004 21:45:43 8,557 enGui.log
27 Oct,2004 11:54:33 47,916 startup.log
dir count = 2, file count = 2
```

- Step 2** To query only command syntax, at the CLI prompt enter **?**, which represents the command name or the command and parameter.

Note If you enter a question mark (?) after a menu command, such as **set**, the question mark functions like the **Tab** key and lists the commands that are available.

Example:

```
admin:file list activelog?Syntax:
file list activelog file-spec [options]
file-spec mandatory file to view
options optional page|detail|reverse|[date|size]
```

End CLI Session

Procedure

To end a CLI session, enter **quit** at the CLI prompt.

If you are logged in remotely, you are logged off and the SSH session is drops. If you are logged in locally, you are logged off and the login prompt returns.

Unsupported VMware Commands

The following list shows the VMware commands currently not supported.

- **show environment fans**
- **show environment power-supply**
- **show environment temperatures**
- **show memory size**
- **show memory count**
- **show memory modules all**
- **utils create report hardware**
- **utils snmp hardware-agents restart**
- **utils snmp hardware-agents start**
- **utils snmp hardware-agents status**
- **utils snmp hardware-agents stop**



CHAPTER 2

CLI Commands

- [Delete Commands, page 5](#)
- [File Commands, page 8](#)
- [Run and Set commands, page 16](#)
- [Show Commands, page 50](#)
- [Unset Commands, page 78](#)
- [Utils Commands, page 80](#)

Delete Commands

delete account

This command allows you to delete an administrator account.

Command Syntax

delete account *account-name*

Syntax Description

Parameters	Description
<i>account-name</i>	The name of an administrator account

Requirements

Command privilege level: 4

Allowed during upgrade: No

delete dns

This command allows you to delete the IP address for a DNS server.

Command Syntax

```
delete dns ip-address
```

Syntax Description

Parameters	Description
<i>ip-address</i>	The IP address of the DNS server that you want to delete.

Usage Guidelines

The system asks whether you want to continue to execute this command.



Caution

If you continue, this command causes a temporary loss of network connectivity.

Requirements

Command privilege level: 1

Allowed during upgrade: No

delete dscp

This command deletes a DSCP port tag.

Command Syntax

```
delete dscp [port-tag]
```

Syntax Description

Parameters	Description
<i>[port-tag]</i>	Represents a DSCP port tag, which is a string that is mapped to a TCP or UDP port to identify the application that uses the port. This value is for the portTag field displayed when you use the command show dscp defaults. The set of port tags is predefined.

Useage Guideline

After you delete an enabled port tag, DSCP marking on that port tag stops. You can recreate a deleted port tag when you use the set dscp marking command; enter the name of the port tag that you previously deleted.

**Tip**

Use the command **show dscp defaults** to list the configured port tags

Command Mode

Administrator (admin:)

delete ipsec

This command allows you to delete IPsec policies and associations.

Command Syntax

delete ipsec policy {ALL| *policy-name*}

association *policy-name* {ALL| *association-name*}

Syntax Description

Parameters	Description
<i>policy-name</i>	An IPsec policy.
<i>association-name</i>	An IPsec association

Requirements

Command privilege level: 1

Allowed during upgrade: No

delete process

This command allows you to delete a particular process.

Command Syntax

delete process *process-id* [**force** | **terminate** | **crash**]

Syntax Description

Parameters	Description
<i>process-id</i>	The process ID number.

Parameters	Description
force	(Optional) Tells the process to stop.
terminate	(Optional) Tells the operating system to terminate the process.
crash	(Optional) Crashes the process and produces a crash dump.

Usage Guidelines

Use the **force** option only if the command alone does not delete the process and use the **terminate** option only if **force** does not delete the process.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

delete smtp

This command allows you to delete the SMTP host.

Command Syntax

delete smtp

Requirements

Command privilege level: 1

Allowed during

File Commands

file check

This command checks the /usr directory tree to see whether any files or directories have been added, removed, or changed in size since the last fresh installation or upgrade and displays the results.

Command Syntax

file check [*detection-size-kb*]

Syntax Description

Parameters	Description
<i>[detection-size-kb]</i>	Specifies the minimum file size change that is required for the command to display the file as changed. Default value: 100 KB.

Usage Guidelines

The command notifies you about a possible impact to system performance and asks you whether you want to continue. The display includes both deleted and new files.

**Caution**

This command can affect system performance. We recommend that you use the command during off-peak hours.

Requirements

Command privilege level: 0

Allowed during upgrade: No

file delete

This command deletes one or more files.

Command Syntax

file delete {**activelog**|**inactivelog**|**install**} *directory/filename* [**detail**] [**noconfirm**]

Syntax Description

Parameters	Description
activelog	A log on the active side.
inactivelog	A log on the inactive side.
install	An installation log.
<i>directory/filename</i>	The path and filename of the files to delete. You can use the wildcard character (*) for "filename".
detail	(Optional) Shows a listing of deleted files with the date and time.
noconfirm	(Optional) Deletes files without asking you to confirm each deletion.

Usage Guidelines



Caution

You cannot recover a deleted file except possibly by using the Disaster Recovery System.

You get prompted for confirmation after entering the command. You cannot delete directories or files that are in use.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

Example

The following example deletes the install log:

```
file delete install install.log
```

file dump

This command dumps the contents of a file to the screen, a page at a time.

Command Syntax

```
file dump {activelog |inactivelog |install } directory/filename [detail] [hex] [recent] [regexpexpression]
```

Syntax Description

Parameters	Description
activelog	A log on the active side.
inactivelog	A log on the inactive side.
install	An installation log
<i>directory/filename</i>	The path and "filename" of the file to dump. You can use the wildcard character (*) for filename as long as it resolves to one file.
detail	(Optional) Displays listing with the date and time.
hex	(Optional) Displays output in hexadecimal.
recent	(Optional) Displays the most recently modified file in the directory.
regexp <i>expression</i>	(Optional) Displays only the lines in the file that match the regular expression

Requirements

Command privilege level: 1 for logs

Allowed during upgrade: Yes

Example

This command dumps contents of file `_cdrIndex.idx`:

```
file dump activelog cm/cdr/_cdrIndex.idx
```

file get

This command sends a log to another system using SFTP.

Command Syntax

```
file get {activelog |inactivelog |install|partBsalog|salog } directory/filename [reltime|abstime]
[match][recurs]
```

Syntax Description

Parameters	Description
activelog	A log on the active side.
inactivelog	A log on the inactive side.
install	An installation log.
partBsalog	The partBsalog log directory.
salog	The salog log directory.
<i>directory/filename</i>	the path to the files to delete. You can use the wildcard character (*) for filename as long as it resolves to one file.
abstime	(Optional) The absolute time period, specified as hh:mm:MM/DD/YY hh:mm:MM/DD/YY.
reltime	(Optional) The relative time period, specified as months weeks days hours minutes value.
match	(Optional) Match a particular string in the filename, specified as string value.
recurs	(Optional) Get all files, including subdirectories.

Usage Guidelines

After the command identifies the specified files, you are prompted to enter an SFTP host, username, and password.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

Examples

This command gets all files in the activelog operating system directory that match the string plat:

```
file get activelog platform match plat
```

This command gets all operating system log files for a particular time period:

```
file get activelog platform/log abstime 18:00:9/27/2005 18:00:9/28/2005
```

file list

This command lists the log files in an available log directory.

Command Syntax

file list {**activelog|inactivelog|install|partBsalog|salog**} *directory/filename*[**page|detail|reverse**] [**date | size**]

Syntax Description

Parameters	Description
activelog	A log on the active side.
inactivelog	A log on the inactive side.
install	An installation log.
partBsalog	The partBsalog log directory.
salog	The salog log directory.
<i>directory</i>	The path to the directory to list. You can use a wildcard character (*) for directory as long as it resolves to one directory.
page	(Optional) Shows the output one screen at a time.
detail	(Optional) Shows a detailed listing with date and time.
reverse	(Optional) Reverse the sort direction.
date	(Optional) Sorts by date.

Parameters	Description
size	(Optional) Sorts by file size.

Requirements

Command privilege level: 1 for logs

Allowed during upgrade: Yes

Examples

This example lists operating system log files with details:

```
file list activelog platform/log page detail
```

This example lists directories created for Emergency Responder logs:

```
file list activelog er/logs
```

This example lists Emergency Responder logs in a specified directory by size:

```
file list activelog er/logs size
```

file search

This command searches the content of a log and displays the matching lines a page at a time.

Command Syntax

```
file search { activelog | inactivelog | install } directory/filename reg-exp [abstime hh:mm:ss mm/dd/yyyy  
hh:mm:ss mm/dd/yyyy] [ignorecase] [retime {days | hours | minutes} timevalue]
```

Syntax Description

Parameters	Description
activelog	A log on the active side.
inactivelog	A log on the inactive side.
install	An installation log.
<i>directory/filename</i>	The path to the files to search. You can use the wildcard character (*) to represent all or part of the filename.
<i>reg-exp</i>	A regular expression.
abstime	(Optional) The files to search based on file creation time. Enter a start time and an end time.
days hours minutes	(Optional) The file age is in days, hours, or minutes.
ignorecase	(Optional) Ignores case when searching

Parameters	Description
reltime	(Optional) The files to search based on file creation time. Enter the age of files to search.
<i>hh:mm:ss mm/dd/yyyy</i>	(Optional) An absolute time, in the format hours:minutes:seconds month/day/year.
<i>timevalue</i>	(Optional) The age of files to search. The unit of this value is specified with the { days hours minutes } option.

Usage Guidelines

Write the search term in the form of a regular expression, which is a special text string for describing a search pattern.

If the search term is found in only one file, the filename appears at the top of the output. If the search term is found in multiple files, each line of the output begins with the filename in which the matching line was found.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

Example

```
file search activelog platform/log/platform.log Err[a-z] ignorecase
```

file tail

This command prints the last few lines of a log file.

Command Syntax

```
file tail {activelog |inactivelog |install } directory/filename[detail] [hex] [lines]
```

Syntax Description

Parameters	Description
activelog	A log on the active side.
inactivelog	A log on the inactive side.
install	An installation log.
<i>directory/filename</i>	The path to the file to tail. You can use the wildcard character (*) for filename as long as it resolves to one file.
detail	(Optional) Long listing with date and time

Parameters	Description
hex	(Optional) Hexadecimal listing
lines	(Optional) Number of lines to display

Requirements

Command privilege level: 1 for logs

Allowed during upgrade: Yes

Example

This example tails the operating system CLI log file:

```
file tail activelog platform/log/cli00001.log
```

file view

This command displays the contents of a file.

Command Syntax

file view {**activelog**|**inactivelog**|**install**|**system-management-log**} *directory/filename*

Syntax Description

Parameters	Description
activelog	A log on the active side.
inactivelog	A log on the inactive side.
install	An installation log.
system-management-log	The contents of the Integrated Management Logs (IML).
<i>directory/filename</i>	The path to the file to view. You can use the wildcard character (*) for filename as long as it resolves to one file.

Usage Guidelines



Caution

Do not use this command to view binary files because this can corrupt the terminal session.

Requirements

Command privilege level: 0
 Allowed during upgrade: Yes

Examples

This example displays the install log:

```
file view install install.log
```

This example displays a particular CDR file:

```
file view activelog er/logs/CERAdmin01.log
```

Run and Set commands

run sql

This command allows you to run an SQL command.

Command Syntax

```
run sql sql_statement
```

Syntax Description

Parameters	Description
<i>sql_statement</i>	The SQL command to run.

Requirements

Command privilege level: 1
 Allowed during upgrade: No

Examples

This example runs an SQL command:

```
run sql select * from cerserver
```

set account

This command sets up a new account on the operating system.

Command Syntax

```
set account name
```

Syntax Description

Parameters	Description
<i>name</i>	The username for the new account.

Usage Guidelines

After you enter the username, the system prompts you to enter the privilege level and password for the new account.

Requirements

Command privilege level: 0

Allowed during upgrade: No

set account enable

This command is used to enable the user account if the account is disabled due to the password inactivity feature.

Password inactivity period is the number of days of inactivity after a password has expired before the account is disabled.

After entering this command, the user account is enabled with current system settings. The system settings are Password min days, Password Max days, Password inactivity period.

Command Syntax

set account enable *userid*

Syntax Description

Parameters	Description
<i>userid</i>	The name of the user account.

Example

This example runs a set account enable command:

```
set account enable test
Enabling the account 'test' with current settings....
.....
Successfully enabled account 'test'
```

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show accountlocking

This command shows the current account locking settings.

Command Syntax

show accountlocking

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set accountlocking disable

This command disables accountlocking for the current administrator accounts.

Command Syntax

set accountlocking disable

Syntax Description

Parameters	Description
disable	Disable account locking.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set accountlocking enable

This command enables accountlocking for the current administrator accounts.

Command Syntax

set accountlocking enable

Syntax Description

Parameters	Description
enable	Enable account locking.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

set accountlocking unlocktime

This command configures the unlock time for Emergency Responder OS administrator accounts in seconds. Acceptable values should be equal to or greater than 300 seconds, but less than 3600 seconds (60 mins).

Command Syntax

set accountlocking unlocktime *seconds*

Syntax Description

Parameters	Description
<i>seconds</i>	The unlocktime in seconds.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set cert delete

This command deletes the certificate test.pem for the unit IPsec.

Command Syntax

set cert delete [*unit*] [*name*]

Syntax Description

Parameters	Description
<i>unit</i>	The name of the trust category.
<i>name</i>	The certificate file name.

Example

```
set cert
  delete ipsec test.pem
```

Requirements

Command privilege level: 1

Allowed during upgrade: No

set cert import

This command imports the certificate for a specific unit | trust.

Command Syntax

set cert import [*unit name*]

Syntax Description

Parameters	Description
<i>unit name</i>	The name of the unit or trust.

Example

The following example runs a set cert import command:

```
set cert
  import trust tomcat
```

Successfully regenerated certificate for tomcat.

Please restart services related to tomcat for the new certificate to become active.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set cert regen

This command regenerates the certificate for the unit.

Command Syntax

set cert regen [*name*]

Parameter

Name is unit name

Syntax Description

Parameters	Description
<i>Name</i>	The name of the unit.

Example

This example runs a set cert regen command:

```
set cert regen tomcat
Successfully regenerated certificate for tomcat.
Please restart services related to tomcat for the new certificate to become active.
```

Requirements

Command privilege level: 1
 Allowed during upgrade: No

set cli pagination

For the current CLI session, this command turns automatic pagination on or off.

Command Syntax

set cli pagination {on | off}

Syntax Description

Parameters	Description
on	Turns pagination on.
off	Turns pagination off.

Requirements

Level privilege: 1
 Command privilege: 1
 Allowed during upgrade: No

Example

```
admin:set cli pagination off
Automatic pagination is turned off
```

set cli session timeout

This command sets the time, in minutes, after which an active CLI session times out and disconnects.

Command Syntax

set cli session timeout*minutes*

Syntax Description

Parameters	Description
<i>minutes</i>	Specifies the time, in minutes, that can elapse before an active CLI session times out and disconnects: <ul style="list-style-type: none"> • Value range: 5-99999 minutes • Default value: 30 minutes

Usage Guidelines

Be aware that the new session timeout value becomes effective immediately for a new CLI session; however, active sessions retain their original timeout value. Also the show cli session timeout command reflects the new value, even if the current session does not use that value.



Note

This setting gets preserved through a software upgrade and does not get reset to the default value.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: No

set commandcount

This command changes the CLI command prompt so that it displays how many CLI commands have executed.

Command Syntax

set commandcount {enable | disable}

Syntax Description

Parameters	Description
enable	Turns on command count.
disable	Turns off command count.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set csr gen

It regenerates the certificate for the unit name.

Command Syntax

set csr gen *name*

Syntax Description

Parameters	Description
<i>name</i>	Specifies the unit on which the certificate is generated.

Example

```
set csr gen tomcat
```

Successfully regenerated certificate for tomcat.

Please restart services related to tomcat for the new certificate to become active.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set date

This command sets the date on the system.

Command Syntax

set date *HH:mm:ss:MM/DD/YY*

Syntax Description

Parameters	Description
<i>HH:mm:ss</i>	Represents the time format (24 hours format).
<i>MM/DD/YY</i>	Represents the date format. This date format is also accepted: MM/DD/YYYY .

Requirements

Command privilege level: 1

Allowed during upgrade: No

Example

To set date and time to 2:10:33 p.m. February 13, 2008:

```
set date 14:10:33:02/13/08
```

set dscp

This command enables or disables DSCP marking on outgoing TCP or UDP packets. You can enable or disable DSCP on a single port tag, or on all port tags at once.

Command Syntax

```
set dscp {enable | disable} {all|port_tag}
```

Syntax Description

Parameters	Description
all	Disables all DSCP port tags.
<i>port_tag</i>	Represents a DSCP port tag, which is a string that is mapped to a TCP or UDP port to identify the application that uses the port. This value is for the portTag field displayed when you use the command show dscp defaults. The set of port tags is predefined.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: No

set dscp defaults

This command sets the factory default DSCP settings for all of the port tags.

Command Syntax

```
set dscp defaults
```

Command Mode

Administrator (admin:)

Useage Guidelines

This command removes all non-default DSCP settings. The command **show dscp defaults** displays the factory default DSCP settings.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set dscp marking

This command sets DSCP markings on port tags by using well-known DSCP classes and numeric values.

Command Syntax

```
set dscp marking port_tag value
```

Syntax Description

Parameters	Description
<i>port_tag</i>	Represents a DSCP port tag, which is a string that is mapped to a TCP or UDP port to identify the application that uses the port. This value is for the portTag field displayed when you use the command show dscp defaults.
<i>value</i>	A DSCP value. You can enter the name of a well-known DSCP class or a numeric value in decimal or hexadecimal format. Precede hexadecimal values with 0x or 0X.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: No

Usage Guidelines

The valid class names as defined by DSCP are:

- **Class Selector:** values CS0, CS1, CS2, CS3, CS5, CS6, CS7 The class selector (CS) values correspond to IP Precedence values and are fully compatible with IP Precedence.
- **Expedited Forwarding:** value EF EF PHB is ideally suited for applications such as VoIP that require low bandwidth, guaranteed bandwidth, low delay, and low jitter.
- **Best Effort:** value BE Also called default PHB, this value essentially specifies that a packet be marked with 0x00, which gets the traditional best-effort service from the network router.
- **Assured Forwarding:** values AF11, AF12, AF13, AF21, AF22, AF23, AF41, AF42, AF43 There are four types of Assured Forwarding classes, each of which has three drop precedence values. These precedence values define the order in which a packet is dropped (if needed) due to network congestion. For example, packets in AF13 class are dropped before packets in the AF12 class.

set ipsec

This command allows you to set IPsec policies and associations.

Command Syntax

set ipsec

policy {ALL | *policy-name*}

association *policy-name* {ALL | *association-name*}

Syntax Description

Parameters	Description
<i>policy-name</i>	An IPsec policy.
<i>association-name</i>	An IPsec association.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set logging

This command allows you to enable or disable logging.

Command Syntax

```
set logging {enable | disable}
```

Syntax Description

Parameters	Description
enable	Turns on logging.
disable	Turns off logging.

Requirements

Command privilege level: 0

Allowed during upgrade: No

set network cluster publisher hostname

This command configures the cluster publisher hostname. Changing the hostname is possible only from the subscriber in a server group. This is supported when migrating from MCS to VMware platforms, but not in any other scenarios.

A temporary loss of network connectivity occurs while the network is being restarted with the new configuration.

Command Syntax

```
set network cluster publisher hostname name
```

Syntax Description

Parameters	Description
<i>name</i>	The hostname to be assigned.

set network cluster publisher ip

This command configures the cluster publisher IP address.

A temporary loss of network connectivity occurs while the network is being restarted with the new configuration.

Command Syntax

```
set network cluster publisher ip addr
```

Syntax Description

Parameters	Description
<i>ip addr</i>	Specifies the ip address of the network cluster.

set network dhcp

This command enables or disables DHCP for Ethernet interface 0. You cannot configure Ethernet interface 1.

Command Syntax

```
set network dhcp eth0 {enable| disable} {node_ip| net_mask| gateway_ip}
```

Syntax Description

Parameters	Description
eth0	Specifies Ethernet interface 0.
enable	This enables DHCP.
disable	This disables DHCP.
<i>node_ip</i>	The new static IP address for the server.
<i>net_mask</i>	The subnet mask for the server.
<i>gateway_ip</i>	The IP address of the default gateway.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, this command causes the system to restart. We recommend that you restart all nodes whenever any IP address gets changed.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set network dns

This command sets the IP address for the primary or secondary DNS server.

Command Syntax

```
set network dns {primary | secondary} ip-address
```

Syntax Description

Parameters	Description
<i>ip-address</i>	The IP address of the primary or secondary DNS server.

Usage Guidelines

The system asks whether you want to continue to execute this command.



Caution

If you continue, this command causes a temporary loss of network connectivity. If you change the IP address of the DNS server, you must restart Cisco Tomcat. For more information, see [utils service](#), on [page 112](#).

Requirements

Command privilege level: 1

Allowed during upgrade: No

set network dns options

This command sets DNS options.

Command Syntax

```
set network dns options [timeout seconds] [attempts number] [rotate]
```

Syntax Description

Parameters	Description
timeout	Sets the DNS request timeout.
<i>seconds</i>	The DNS timeout period, in seconds.
attempts	Sets the number of times to attempt a DNS request before quitting.
<i>number</i>	Specifies the number of attempts.

Parameters	Description
rotate	Causes the system to rotate among the configured DNS servers, distributing the load.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

set network domain

This command sets the domain name for the system.

Command Syntax

set network domain *domain-name*

Syntax Description

Parameters	Description
<i>domain-name</i>	The system domain that you want to assign.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, this command causes a temporary loss of network connectivity.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set network failover

This command enables and disables network fault tolerance.

Command Syntax

failover {enable | disable}

Syntax Description

Parameters	Description
enable	Enables network fault tolerance.
disable	Disables network fault tolerance.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set network gateway

This command enables you to configure the IP address of the network gateway.

Command Syntax

set network gateway *ip-address*

Syntax Description

Parameters	Description
<i>ip-address</i>	The IP address of the network gateway that you want to assign.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, this command causes the system to restart.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set network hostname

This command allows an administrator to set the network host name, change the IP address of the node, and restart the system.

Before attempting this command, the administrator should have a valid DRF backup.

Command Syntax

set network hostname *hostname*

Syntax Description

Parameters	Description
<i>hostname</i>	<p>Represents the new network hostname of the system.</p> <p>Note The host name must follow the rules for ARPANET host names. It must start with an alphabetic character, end with an alphanumeric character, and consist of alphanumeric characters and hyphens. The host name can have a maximum length of 63 characters.</p>

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: No

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, this command causes the system to restart.

Example

```
admin:set network hostname
WARNING: Changing this setting will invalidate software license on this server. The license
will have to be re-hosted.
Continue (y/n):
Continue (y/n)?y
```

ctrl-c: To quit the input.

*** W A R N I N G ***

Do not close this window without first canceling the command.

This command will automatically restart system services.
The command should not be issued during normal operating hours.

```
=====
Note: Please verify that the new hostname is a unique
name across the cluster and, if DNS services are
utilized, any DNS configuration is completed
before proceeding.
=====
```

Security Warning : This operation will regenerate
all CUCM Certificates including any third party

```

signed Certificates that have been uploaded.

Enter the hostname:: app-lfwelty5
Would you like to change the network ip address at this time [yes]::

Warning: Do not close this window until command finishes.

ctrl-c: To quit the input.

*** W A R N I N G ***
=====
Note: Please verify that the new ip address is unique
across the cluster.
=====

Enter the ip address:: 106.1.34.154
Enter the ip subnet mask:: 255.0.0.0
Enter the ip address of the gateway:: 106.1.1.1
Hostname: app-lfwelty5
IP Address: 106.1.34.154
IP Subnet Mask: 255.0.0.0
Gateway: 106.1.1.1

Do you want to continue [yes/no]? yes
...

```

**Note**

The administrator can change both the hostname and IP address by responding **yes**. To change just the hostname, respond **no**.

set network ip

This command sets the IP address for Ethernet interface 0. You cannot configure Ethernet interface 1.

Command Syntax

```
set network ip eth0 ip-address ip-mask
```

Syntax Description

Parameters	Description
eth0	Specifies Ethernet interface 0.
ip-address	The IP address that you want assign.
ip-mask	The IP mask that you want to assign.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, this command causes the system to restart.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set network max_ip_contrack

This command sets the ip_contrack_max value.

Command Syntax

```
set network max_ip_contrack ip_contrack_max
```

Syntax Description

Parameters	Description
<i>ip_contrack_max</i>	Specifies the value for ip_contrack_max.

set network mtu

This command sets the maximum MTU value.

Command Syntax

```
set network mtu mtu_max
```

Syntax Description

Parameters	Description
<i>mtu_max</i>	Specifies the maximum MTU value. Note The system default MTU value equals 1500.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, the system temporarily loses network connectivity.

Requirements

Level privilege: 1

Command privilege: 1

Allowed during upgrade: No

Example

```

admin:set network mtu 576          ***  W A R N I N G  ***
This will cause the system to temporarily lose network connectivity

        Do you want to continue?

Enter "yes" to continue or any other key to abort

yes
executing...

```

set network nic

This command sets the properties of the Ethernet interface 0. You cannot configure Ethernet interface 1.

Command Syntax

```
set network nic eth0 {auto { en | dis }} {speed | {10 | 100}} {duplex | {half | full}}
```

Syntax Description

Parameters	Description
eth0	Specifies Ethernet interface 0.
auto	Specifies whether auto negotiation gets enabled or disabled.
speed	Specifies the speed of the Ethernet connection: 10 or 100 Mbps.
duplex	Specifies half-duplex or full-duplex.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, this command causes a temporary loss of network connections while the NIC gets reset.

**Note**

You can enable only one active NIC at a time.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set network ntp option

This command adds a noquery option to /etc/config file.

Command Syntax

```
set network ntp option noquery
```

set network pmtud

This command enables and disables path MTU discovery.

Command Syntax

```
set network pmtud {enable | disable}
```

Syntax Description

Parameters	Description
enable	Enables Path MTU Discovery.
disable	Disables Path MTU Discovery.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, the system temporarily loses network connectivity.

Requirements

Level privilege: 1

Command privilege: 1

Allowed during upgrade: No

Example

This example runs the set network pmtud command.

```
admin:set network pmtud enable
***  W A R N I N G  ***
This will cause the system to temporarily lose network connectivity
```

```

Do you want to continue?
Enter "yes" to continue or any other key to abort
yes
executing...
admin:

```

set network restore

This command configures the specified Ethernet port to use a specified static IP address.



Caution

Only use this command option if you cannot restore network connectivity using any other **set network** commands. This command deletes all previous network settings for the specified network interface, including network fault tolerance. After running this command, you must restore your previous network configuration manually.



Caution

The server temporarily loses network connectivity when you use this command.

Command Syntax

```
set network restore eth0 ip-address network-mask gateway
```

Syntax Description

Parameters	Description
eth0	Specifies Ethernet interface 0.
<i>ip-address</i>	Specifies the IP address.
<i>network-mask</i>	Specifies the subnet mask.
<i>gateway</i>	Specifies the IP address of the default gateway.

Requirements

Command privilege level: 0
 Allowed during upgrade: Yes

set network status

This command sets the status of Ethernet 0 to up or down. You cannot configure Ethernet interface 1.

Command Syntax

```
set network status eth0 {up | down}
```

Syntax Description

Parameters	Description
eth0	Specifies Ethernet interface 0.
up	Sets the status of Ethernet interface 0 to up.
down	Sets the status of Ethernet interface 0 to down.

Usage Guidelines

The system asks whether you want to continue to execute this command.

**Caution**

If you continue, the system temporarily loses network connectivity.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set password

This command allows you to change the administrator password.

Command Syntax

```
set password {admin | security}
```

Syntax Description

Parameters	Description
admin	Administrator.
security	Security.

Usage Guidelines

The system prompts you for the old and new passwords.

The password must contain at least six characters, and the system checks it for strength.

Servers in a cluster use the security password to authenticate communication between servers. You must reset the cluster after you change the security password.

To change a password:

- 1 Change the security password on the publisher server and then reboot the server.

- 2 Change the security password on all the subscriber servers to the same password that you created on the publisher server and restart the subscriber server to propagate the password change.

**Note**

We recommend that you restart each server after the password is changed on that server.

**Caution**

Failure to reboot the servers causes system service problems and problems with the Emergency Responder Administration on the subscriber servers.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set password age minimum

This command modifies the value of minimum password age for OS admin accounts in days.

Usage Guidelines

Acceptable values should be equal to or greater than 0 days but less or equal to 10 days.

Command Syntax

set password age minimum *days*

Syntax Description

Parameters	Description
<i>days</i>	The minimum password age in days.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set password age maximum

This command modifies the value of maximum password age for Emergency Responder OS administration accounts in days.

Command Syntax

set password age maximum *days*

Usage Guidelines

Acceptable values should be equal to or greater than 10 days but less than 3650 days (10 years).

Syntax Description

Parameters	Description
<i>days</i>	The maximum password age in days.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set password complexity character disable

This command disables password complexity. Changes take effect only at the next password change.

When disabled, the password created or changed after executing the command is no longer strong. The password does not need uppercase, lowercase, digit and special characters.

Command Syntax

set password complexity character disable

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set password complexity character enable

This command enables password complexity rules for the type of characters in a password.

When enabled, the passwords need to follow these guidelines:

- It must have at least one lowercase character.
- It must have at least one uppercase, one digit, and one special character.
- All of the adjacent characters on the keyboard are not accepted.
- Any of the previous ten passwords cannot be reused.
- The admin user password can only be changed once in 24 hours.
- A violation of any of the preceding rules results in a failure.

Command Syntax

set password complexity character enable

Requirements

Command privilege level: 1

Allowed during upgrade: No

set password complexity minimum-length

This command modifies the value of minimum password length for Unified CM OS accounts.

Command Syntax

set password complexity minimum-length *length*

Syntax Description

Parameters	Description
<i>length</i>	The minimum password length.

Useage Guidelines

Acceptable values should be equal to or greater than 6. Use this command only after enabling the character complexity of passwords.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set password expiry maximum-age

This command enables or disables the password expiry maximum age settings for Cisco Unified Operating System Administrator accounts.

Command Syntax

set password expiry maximum-age {enable|disable}

Syntax Description

Parameters	Description
enable	Turns on password expiry maximum age settings for Cisco Unified Operating System administrator accounts. The set password expiry enable command sets the value of maximum password age to 3650 days (10 yrs) for Cisco Unified Operating System Administrator accounts.

Parameters	Description
disable	Turns off password expiry maximum age settings for Cisco Unified Operating System administrator accounts. The set password expiry disable command results in Cisco Unified Operating System Administrator accounts never expiring.

set password expiry minimum-age enable

This command enables minimum password expiry for OS accounts.

Usage Guidelines

This command sets the value of minimum password age to 1 day (24 hrs) for OS administration accounts.

Command Syntax

set password expiry minimum-age enable.

set password expiry minimum-age disable

This command is used to disable minimum password aging for OS accounts.

This means passwords for OS admin accounts can be changed at any interval.

Command Syntax

set password expiry minimum-age disable

set password expiry user maximum-age disable

This command disables password expiry for a particular OS account.

Command Syntax

set password expiry user maximum-age disable *userid*

Syntax Description

Parameters	Description
<i>userid</i>	The name of account for which to disable maximum password age settings.

set password expiry user maximum-age enable

This command enables maximum password expiry for a particular OS account.

Command Syntax

set password expiry user maximum-age enable *userid*

Syntax Description

Parameters	Description
<i>userid</i>	The name of account for which to enable maximum password age settings.

set password expiry user minimum-age disable

This command disables minimum password age settings for a particular OS account.

Command Syntax

set password expiry user minimum-age disable *userid*

Syntax Description

Parameters	Description
<i>userid</i>	The account for which to disable minimum password age settings.

set password expiry user minimum-age enable

This command enables minimum password age for a particular OS account.

Command Syntax

set password expiry user minimum-age enable *userid*

Syntax Description

Parameters	Description
<i>userid</i>	The account for which to enable minimum password age settings.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set password history

This command sets the number of passwords to maintain in history.

Command Syntax

set password history *number*

Syntax Description

Parameters	Description
<i>number</i>	The number of passwords to maintain in history.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set password inactivity disable

This command disables the password inactivity for the OS accounts.

Command Syntax

set password inactivity disable

set password inactivity enable

This command enables the password inactivity for the OS accounts with the default value set as 10 days.

Command Syntax

set password inactivity enable

set password inactivity period

This command sets the password inactivity for the OS accounts with the configured value.

Command Syntax

set password inactivity period *days*

Syntax Description

Parameters	Description
<i>days</i>	The number of days for which to set inactivity. Acceptable values are 1 to 99 days.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set password user admin

This commands sets a new administration password.

Command Syntax

set password user admin

Example

This example runs the set password user admin command:

```
set password user admin
Please enter the old password :*****
Please enter the new password:*****
re-enter new password to confirm:*****
```

Requirements

Command privilege level: 1

Allowed during upgrade: No

set password user security

This command sets a new platform security password.

Command Syntax

set password user security

Example

This example runs the set password user security command:

```
set password user security
Please enter the password:*****
re-enter the password to confirm: *****
```

Requirements

Command privilege level: 1

Allowed during upgrade: No

set session maxlimit

This command sets the upper limit for concurrent sessions.

Command Syntax**set session maxlimit** *[value]***Syntax Description**

Parameters	Description
maxlimit	This command sets the upper limit for concurrent sessions. Acceptable values are 1 - 100. If no upper limit is entered, the default value of 10 is assigned to sshd_config param.
<i>[value]</i>	Acceptable values are 1 - 100.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

set smtp

This command sets the SMTP server hostname.

Command Syntax**set smtp** *hostname***Syntax Description**

Parameters	Description
<i>hostname</i>	The SMTP server name.

Requirements

Command privilege level: 0

Allowed during upgrade: No

set timezone

This command changes the system time zone.

Command Syntax

set timezone *timezone*

Usage Guidelines

Enter enough characters to uniquely identify the new time zone. Be aware that the time zone name is case-sensitive.

**Note**

You must restart the system after you change the time zone.

Syntax Description

Parameters	Description
<i>timezone</i>	The new timezone.

Requirements

Command privilege level: 0

Allowed during upgrade: No

Example

This example sets the time zone to Pacific time:

```
set timezone Pac
```

set trace

This command sets trace activity for the specified task.

Command Syntax

set trace {**enable Error**| **enable Special**| **enable State_Transition**| **enable Significant**| **enable Entry_exit**| **enable Arbitrary**| **enable Detailed**| **disable**} *tname*

Syntax Description

Parameters	Description
<i>tname</i>	The task for which you want to enable or disable traces.
enable Error	Sets task trace settings to the error level.
enable Special	Sets task trace settings to the special level.
enable State_Transition	Sets task trace settings to the state transition level.
enable Significant	Sets task trace settings to the significant level.
enable Entry_exit	Sets task trace settings to the entry_exit level.
enable Arbitrary	Sets task trace settings to the arbitrary level.
enable Detailed	Sets task trace settings to the detailed level.
disable	Disables the task trace settings.

Requirements

Command privilege level: 1

Allowed during upgrade: No

set web-security

This command sets the web security certificate information for the operating system.

Command Syntax

set web-security *orgunit orgname locality state [country] [alternate-host-name]*

Usage Guidelines

When you set an *alternate-host-name* parameter with the **set web-security** command, self-signed certificates for Tomcat contains the Subject Alternate Name extension with the alternate host name specified. CSR for Emergency Responder contains Subject Alternate Name Extension with the alternate host name included in the CSR.

Syntax Description

Parameters	Description
<i>orgunit</i>	The organizational unit.
<i>orgname</i>	The organizational name.

Parameters	Description
<i>locality</i>	The organization location.
<i>state</i>	The organization state.
<i>country</i> represents	The organization country.
<i>alternate-host-name</i>	(Optional) Specifies an alternate name for the host when you generate a web-server (Tomcat) certificate.

Requirements

Command privilege level: 0

Allowed during upgrade: No

set webapp session timeout

This command sets the time, in minutes, that can elapse before a web application, such as Cisco emergency responder, times out and logs off the user.

For the new webapp session timeout setting to become effective, you must restart the Cisco Tomcat service. Until you restart the Cisco Tomcat service, the show webapp session timeout command reflects the new values, but system continues to use and reflect the old values. This command prompts you to restart the service.



Caution

Restarting the Cisco Tomcat service ends all active sessions and can affect system performance. Cisco recommends that you only execute this command during off-peak traffic hours.



Note

This setting gets preserved through a software upgrade and does not get reset to the default value.

Command Syntax

set webapp session timeout *minutes*

Syntax Description

Parameters	Description
<i>minutes</i>	Specifies the time, in minutes, that can elapse before a web application times out and logs off the user. <ul style="list-style-type: none"> Value range: 5-99999 minutes Default value: 30 minutes

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: No

set workingdir

This command sets the working directory for active, inactive, and installation logs.

Command Syntax

`set workingdir {activelog| inactivelog| install} directory`

Syntax Description

Parameters	Description
<code>activelog</code>	Sets the working directory for active logs.
<code>inactivelog</code>	Sets the working directory for inactive logs.
<code>install</code>	Sets the working directory for installation logs.
<i>directory</i>	The current working directory.

Requirements

Command privilege level: 0 for logs

Allowed during upgrade: Yes

Show Commands

show account

This command lists current administrator accounts, except the master administrator account.

Command Syntax

`show account`

Requirements

Command privilege level: 4

Allowed during upgrade: Yes

show cert

This command displays certificate contents and certificate trust lists.

Command Syntax

Table 1: Available Commands

Command	Result
<code>show cert list {own trust}</code>	This command displays certificate trust lists.
<code>show cert own <i>filename</i></code>	This command displays certificate contents.
<code>show cert trust <i>filename</i></code>	This command displays certificate contents.

Syntax Description

Parameters	Description
<i>filename</i>	The name of the certificate file.
own	Specifies owned certificates.
trust	Specifies trusted certificates.
list	Specifies a certificate trust list.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

Example

This command displays own certificate trust lists:

```
show cert list own
```

show cli pagination

This command displays the status of the automatic CLI pagination.

Command Syntax**show cli pagination****Requirements**

Level privilege: 0

Command privilege: 0

Allowed during upgrade: Yes

Example

The following example runs the show cli pagination command:

```
admin: show cli paginationAutomatic Pagination: Off.
```

show cli session timeout

This command displays the CLI session timeout value, which is the amount of time, in minutes, that can elapse before a CLI session times out and disconnects.

Command Syntax**show cli session timeout****Command Mode**

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show csr list

This command displays the selected CSR file.

Command Syntax**show csr list *type*****Example**

This example runs a show csr list command:

```
show csr list own
```

```
tomcat/tomcat.csr
```

```
Vipr-QuetzalCoatl/Vipr-QuetzalCoatl.csr
```

show ctl

This command displays the contents of the Certificate Trust List (CTL) file on the server, and it notifies you if the CTL is not valid.

Command Syntax

```
show ctl
```

show date

This command shows the system date.

Command Syntax

```
show date
```

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show diskusage

This command displays information about disk usage on the server.

Command Syntax

```
show diskusage activelog {activelog| common| inactivelog| install| tmp} filename filename {directory | sort}
```

Syntax Description

Parameters	Description
activelog	Displays disk usage information about the activelog directory.
common	Displays disk usage information about the common directory.
inactivelog	Displays disk usage information about the inactivelog directory.
install	Displays disk usage information about the install directory.
tmp	Displays disk usage information about the tmp directory.
filename <i>filename</i>	(Optional) Saves the output to a file specified by a filename. These files are stored in the platform/cli directory. To view saved files, use the file view activelog command.

Parameters	Description
directory	(Optional)Displays only the directory sizes.
sort	(Optional)Sorts the output based on file size. File sizes are displayed in 1024-byte blocks.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show dscp all

This command displays the current DSCP traffic markings on all the ports. It displays the DSCP markings in decimal and hexadecimal. If the value corresponds to a class then it displays the correct class. If the value does not correspond to a class, then it displays N/A.

Command Syntax

```
show dscp all
```

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: No

show dscp defaults

This command displays the default factory DSCP settings. These values take effect if the **set dscp defaults** command is executed.

Command Syntax

```
show dscp defaults
```

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: No

show dscp marking

This command displays the current DSCP traffic markings for a particular DSCP value.

Command Syntax

show dscp marking *value*

Syntax Description

Parameters	Description
<i>value</i>	DSCP value. You can enter the name of a well-known DSCP class, or a numeric value in decimal or hexadecimal format. Precede hexadecimal values with 0x or 0X.

Usage Guidelines

The valid class names as defined by DSCP are:

- Class Selector: values CS0, CS1, CS2, CS3, CS5, CS6 CS7 The class selector (CS) values correspond to IP Precedence values and are fully compatible with IP Precedence.
- Expedited Forwarding: value EF EF PHB is ideally suited for applications such as VoIP that require low bandwidth, guaranteed bandwidth, low delay, and low jitter.
- Best Effort: value BE Also called default PHB, this value essentially specifies that a packet be marked with 0x00, which gets the traditional best-effort service from the network router.
- Assured Forwarding: values AF11, AF12, AF13, AF21, AF22, AF23, AF41, AF42, AF43 There are four types of Assured Forwarding classes, each of which has three drop precedence values. These precedence values define the order in which a packet is dropped (if needed) due to network congestion. For example, packets in AF13 class are dropped before packets in the AF12 class.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show dscp status

This command displays the current DSCP traffic markings.

Command Syntax

show dscp status {**enabled|disabled**}

Syntax Description

Parameters	Description
enabled	Filters the output to show only DSCP traffic markings that are enabled. If you do not specify a status, this filter is the default option.
disabled	Filters the output to show only DSCP traffic markings that are disabled.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: No

show environment

This command displays information about the server hardware.

Command Syntax

show environment {fans |power-supply |temperatures}

Syntax Description

Parameters	Description
fans	Displays information gathered by fan probes.
power-supply	Displays information gathered by power supply probes.
temperatures	Displays information gathered by temperature probes.

show hardware

This command displays the following information about the platform hardware.

Command Syntax

show hardware

Usage Guidelines

This command displays the following information about the platform hardware:

- Platform
- Serial number
- BIOS build level
- BIOS manufacturer
- Active processors
- RAID controller status

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show ipsec

This command displays information about IPsec policies and associations.

Command Syntax

Table 2: Available Commands

Command	Result
show ipsec information <i>policy_group policy_name</i>	This command displays detailed information about the specified ipsec policy.
show ipsec policy_group	This command displays all the ipsec policy group on the node.
show ipsec policy_name <i>policy_group</i>	This command displays the list of ipsec policy names that exist in the specified policy group.
show ipsec status	

Syntax Description

Parameters	Description
information	Displays the association details and status for the policy.
status	Displays the status of all IPsec tunnels that are defined in the system.
<i>policy_group</i>	The name of a specific IPsec policy.

Requirements

Command privilege level: 1

Allowed during upgrade: yes

Example

This example displays IPsec policies:

```
show ipsec policy
```

show logins

This command displays recent logins to the server.

Command Syntax

```
show logins number
```

Syntax Description

Parameters	Description
<i>number</i>	The number of most recent logins to display. The default is 20.

show memory

This command displays information about the server memory.

Command Syntax

```
show memory {count| module[ALL | module_number]| size}
```

Syntax Description

Parameters	Description
ALL	Displays information about all installed memory modules.
<i>module_number</i>	Specifies the memory module to display.
count	(Optional)Displays the number of memory modules on the system.
module	(Optional)Displays detailed information about each memory module.
size	(Optional)Displays the total amount of memory.

show myself

This command displays information about the current account.

Command Syntax

show myself

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show network

This command displays network information.

Command Syntax

Table 3: Available Commands

Command	Result
show networkall [detail]	This command shows network information for listening and non-listening sockets.
show networketh0 [detail]	This command shows network information for ethernet 0.
show networkfailover [detail] [page]	This command shows Network Fault Tolerance information.
show networkroute [detail]	This command shows network routing information.
show network status [detail] [listen] [process] [all] [nodns] [search stext]	This command shows active internet connections.
show network ip_contrack	This command shows ip_contrack usage information.
show network max_ip_contrack	This command shows max_ip_contrack information.
show network dhcp eth0 status	This command shows DHCP status information.
show network cluster	This command lists nodes in the network cluster.
show network ipprefs {all enabled public	This command shows the list of ports that have been requested to be opened or translated in the firewall.

Command	Result
show network ntp	
show network failover[detail][page]	This command shows Network Fault Tolerance information.
show network ipv6{route settings}	This command shows IPv6 network routes and network settings.

Syntax Description

Parameters	Description
eth0	Specifies Ethernet 0.
failover	Specifies Network Fault Tolerance information.
route	Specifies network routing information.
status	Specifies active Internet connections.
ip_contrack	Specifies ip_contrack usage information.
max_ip_contrack	Specifies max_ip_contrack information.
dhcp eth0 status	Displays DHCP status information.
all	Specifies all basic network information.
options	(Optional)Displays additional information.
detail	(Optional)Displays more detailed additional information.
page	(Optional)Displays information one page at a time.
listen	(Optional)Displays only listening sockets.
process	(Optional)Displays the process ID and name of the program to which each socket belongs.
all	(Optional)Displays both listening and nonlistening sockets.
nodns	(Optional)Displays numerical addresses without any DNS information.
search stext	(Optional)Searches for the stext in the output.

Usage Guidelines

The **eth0** parameter displays Ethernet port 0 settings, including DHCP and DNS configurations and options.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

Example

This example displays active Internet connections:

```
show network status
```

show network cluster

This command lists nodes in the network cluster.

Command Syntax

```
show network cluster
```

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show network ipprefs

This command displays the list of ports that have been requested to be opened or translated in the firewall.

Command Syntax

```
ipprefs {all| enabled| public}
```

Syntax Description

Parameters	Description
all	Displays all incoming ports that may be used on the product.
enabled	Displays all incoming ports that are currently opened.
public	Displays all incoming ports that are currently opened for any remote client.

Requirements

Level privilege: 0

Command privilege: 0

Allowed during upgrade: Yes

Example

The following example shows show the network ipprefs command:

```
admin:show network ipprefs public
Application IPProtocol PortValue Type XlatedPort Status Description
-----
sshhd tcp 22 public - enabled sftp and ssh access
tomcat tcp 8443 translated 443 enabled secure web access
tomcat tcp 8080 translated 80 enabled web access
clm udp 8500 public - enabled cluster manager
clm tcp 8500 public - enabled cluster manager
ntpd udp 123 public - enabled network time sync
snmpdm udp 161 public - enabled SNMP
ccm tcp 2000 public - enabled SCCP-SIG
ctftp udp 6969 translated 69 enabled TFTP access to CUCM TFTP
Server
ctftp tcp 6970 public - enabled HTTP access to CUCM TFTP
Server
admin:
```

set network ntp option

This command adds a noquery option to /etc/config file.

Command Syntax

```
set network ntp option noquery
```

show open

This command displays open files and ports on the system.

Syntax Description

Table 4: Available Commands

Command	Result
<code>show open files [all] [process processID] [regex reg_exp]</code>	This command shows open files on the system.
<code>show open ports [all] [regex reg_exp]</code>	This command shows all open ports on the system.

Syntax Description

Parameters	Description
files	displays open files on the system.
ports	displays open ports on the system.
all	(Optional)Displays all open files or ports.
process	(Optional)Displays open files that belong to the specified process.
<i>processID</i>	(Optional)Specifies a process.
regex	(Optional)Displays open files or ports that match the specified regular expression.
<i>reg_exp</i>	(Optional)A regular expression.

show packages

This command displays the name and version for installed packages.

Command Syntax

show packages {*active*|*inactive*} *name* [*page*]

Syntax Description

Parameters	Description
active	Specifies active packages.
inactive	Specifies inactive packages.
<i>name</i>	The package name. To display all active or inactive packages, use the wildcard character (*).
page	(Optional)Displays the output one page at a time.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show password expiry maximum-age

This command displays the configured password expiration parameters.

Command Syntax

```
show password expiry maximum-age
```

show password expiry minimum-age

This command displays the configured password expiration parameters.

Command Syntax

```
show password expiry minimum-age
```

show password expiry user maximum-age

This command displays the configured password expiration parameters for a particular OS user.

Command Syntax

```
show password expiry user maximum-age userid
```

show password expiry user minimum-age

This command displays the configured password expiration parameters for a particular OS user.

Command Syntax

```
show password expiry user minimum-age userid
```

show password history

This command displays the number of passwords that are maintained in the history for OS admin accounts.

Command Syntax

```
show password history
```

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show password inactivity

This command displays the status of the password inactivity for OS accounts.

Password inactivity is the number of days of inactivity after a password has expired before the account is disabled.

Command Syntax

show password inactivity

Example

```
show password inactivity
Password Inactivity: Enabled and is currently set to 10
                    days
```

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show process

This command displays information about processes running on the system.

Syntax

Command	Result
show processlist [file filename] [detail]	This command displays a list of all the processes and critical information about each process and visually indicates the child-parent relationships between the processes.
show processload [cont] [clear] [noidle] [num number] [thread] [cpu memory] [time] [page]	This command displays the current load on the system.
show process name process [file filename]	This command displays the details of processes that share the same name and indicates their parent-child relationship.
show process open-fd process-id [, process-id2]	This command lists the open file descriptors for a comma-separated list of process IDs.
show process search regexp [file filename]	This command searches for the pattern that the regular expression regexp specifies in the output of the operating system-specific process listing.

Command	Result
show process using-most cpu [<i>number</i>] [file <i>filename</i>]	This command displays a list of the most CPU-intensive processes.
show process using-most memory [<i>number</i>] [file <i>filename</i>]	This command displays a list of the most memory-intensive processes.
show process pid <i>pid</i> [file <i>filename</i>]	This command displays a list of PIDs.
show process user <i>username</i> [file <i>filename</i>]	This command retrieves details of processes that share the user name and displays parent-child relationship.
show process using most	This command lists the most intensive processes.

Syntax Description

Parameters	Description
list	displays a list of all the processes and critical information about each process, and visually indicates the child-parent relationships between the processes.
load	displays the current load on the system.
name	displays the details of processes that share the same name and indicates their parent-child relationship.
open-fd	lists the open file descriptors for a comma-separated list of process IDs.
search	searches for the pattern specified by the regular expression <i>regex</i> in the output of the operating system-specific process listing.
using-most cpu	displays a list of the most CPU-intensive processes.
using-most memory	displays a list of the most memory-intensive processes.
file <i>filename</i>	(Optional)Outputs the results to the file specified by the filename.
detail	(Optional)Displays the detailed output.
cont	(Optional)Repeats the command continuously.
clear	(Optional)Clears the screen before displaying output.
noidle	(Optional)Ignores the idle/zombie processes.

Parameters	Description
num number	(Optional)Displays the number of processes specified by number. The default number of processes is 10. Set number to all to display all processes.
thread	(Optional)Displays threads.
[cpu memory time]	(Optional)Sorts output by CPU usage, memory usage, or time usage. The default is to sort by CPU usage.
page	(Optional)Displays the output in pages.
<i>process</i>	(Optional)Specifies the name of a process.
<i>process-id</i>	(Optional)Specifies the process ID number of a process.
<i>regex</i>	(Optional)A regular expression.
<i>number</i>	(Optional)The number of processes to display. The default is 5.
<i>pid</i>	Specifies the process ID number of a process.
<i>username</i>	Specifies the username.

show session maxlimit

This command shows the upper limit for concurrent SSH sessions.

Command Syntax

```
show session maxlimit
```

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show smtp

This command displays the name of the SMTP host.

Command Syntax**show snmp****Requirements**

Command privilege level: 0

Allowed during upgrade: Yes

show stats io

This command displays system I/O statistics.

Command Syntax**show stats io** [**kilo**] [**detail**] [**page**] [**file** *filename*]**Syntax Description**

Parameters	Description
kilo	Displays statistics in kilobytes.
detail	Displays detailed statistics on every available device on the system and overrides the kilo option.
page	Displays one page at a time.
file <i>filename</i>	Outputs the information to a file.

Usage Guidelines

The file option saves the information to
`platform/cli/filename.txt`.

The filename cannot contain the "." character.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show status

This command displays basic platform status.

Command Syntax**show status****Usage Guidelines**

This command displays the following basic platform status:

- Host name
- Date
- Time zone
- Locale
- Product version
- Platform version
- CPU usage
- Memory and disk usage

Requirements

Command privilege level: 0

show tech all

This command displays the combined output of all **show tech** commands.

Command Syntax

show tech all [**page**] [**file filename**]

Syntax Description

Parameters	Description
page	Displays one page at a time.
filefilename	Outputs the information to a file.

Usage Guidelines

The file option saves the information to `platform/cli/filename.txt`.
The file name cannot contain the "." character.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech database

This command creates a CSV file of the entire database.

Command Syntax

```
show tech database {dump|sessions}
```

Syntax Description

Parameters	Description
dump	Creates a CSV file of the entire database.
sessions	Redirects the session and SQL information of the present session IDs to a file.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech database dump

This command creates a CSV file of the entire database.

Command Syntax

```
show tech database dump
```

show tech dbintegrity

This command displays the database integrity.

Command Syntax

```
show tech dbintegrity
```

show tech dbinuse

This command displays the database in use.

Command Syntax

```
show tech dbinuse
```

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech dbschema

This command displays the database schema in a CSV file.

Command Syntax

```
show tech dbschema
```

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech dbstateinfo

This command displays the state of the database.

Command Syntax

```
show tech dbstateinfo
```

show tech network

This command displays network aspects of the server.

Command Syntax

Command	Result
<code>show tech network</code>	
<code>show tech network [page] [file filename]</code>	This command displays network tech information for a page.
<code>show tech network all [page] [search text] [file filename]</code>	This command displays all network tech information.
<code>show tech network hosts [page] [search text] [file filename]</code>	This command displays information about hosts configuration.
<code>show tech network interfaces [page] [search text] [file filename]</code>	This command displays information about the network interfaces.
<code>show tech network resolv [page] [search text] [file filename]</code>	This command displays information about hostname resolution.
<code>show tech network routes [page] [search text] [file filename]</code>	This command displays information about network routes.

Command	Result
show tech network sockets {numeric}	This command displays the list of open sockets.

Syntax Description

Parameters	Description
all	displays all network technical information.
hosts	displays information about hosts configuration.
interfaces	displays information about the network interfaces.
resolv	displays information about hostname resolution.
routes	displays information about network routes.
sockets	displays the list of open sockets.
page	(Optional)Displays one page at a time.
search <i>text</i>	(Optional)Searches the output for the string specified by text. The search is not case sensitive.
file <i>filename</i>	(Optional)Outputs the information to a file.
numeric	(Optional)Displays the numerical addresses of the ports instead of determining symbolic hosts. It is equivalent to running the Linux netstat [-n] shell command.

Usage Guidelines

The **file** option saves the information to platform/cli/filename.txt. The file name cannot contain the "." character.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech prefs

This command displays all preferences files for Emergency Responder and its database.

Usage Guidelines

This information is written to a file, which can be viewed subsequently using the **file view** CLI.

Command Syntax

```
show tech prefs
```

show tech runtime

This command displays server runtime.

Command Syntax

```
show tech runtime {all | cpu | disk | env | memory} [page] [file filename]
```

Syntax Description

Parameters	Description
all	Displays all runtime information.
cpu	Displays CPU usage information at the time the command is run.
disk	Displays system disk usage information.
env	Displays environment variables.
memory	Displays memory usage information.
page	Displays one page at a time.
file filename	Outputs the information to a file.

Usage Guidelines

The **file** option saves the information to `platform/cli/filename.txt`.
The file name cannot contain the "." character.

Requirements

Command privilege level: 1
Allowed during upgrade: Yes

show tech systables

This command displays the name of all tables in the sysmaster database.

Command Syntax

```
show tech systables
```

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech system

This command displays the system aspects of the server.

Command Syntax

show tech system {all| bus| hardware| host| kernel| software| tools} [page] [file *filename*]

Syntax Description

Parameters	Description
all	Displays all of the system information.
bus	Displays information about the data buses on the server.
hardware	Displays information about the server hardware.
host	Displays information about the server.
kernel	Lists the installed kernel modules.
software	Displays information about the installed software versions.
tools	Displays information about the software tools on the server.
page	Displays one page at a time.
file <i>filename</i>	Outputs the information to a file.

Usage Guidelines

The **file** option saves the information to `platform/cli/filename.txt`. The file name cannot contain the "." character.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech table

This command displays the contents of the specified database table.

Command Syntax

```
show tech table table_name [page] [csv]
```

Syntax Description

Parameters	Description
<i>table_name</i>	The name of the table to display.
page	Displays the output one page at a time.
csv	Sends the output to a comma separated values file.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show tech version

This command displays the version of the installed components.

Command Syntax

```
show tech version [page]
```

Syntax Description

Parameters	Description
page	Displays the output one page at a time.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

show timezone

This command displays time zone information.

Command Syntax

```
show timezone {config|list} [page] }
```

Syntax Description

Parameters	Description
config	Displays the current time zone settings.
list	Displays the available time zones.
page	Displays the output one page at a time.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show trace

This command displays trace information for a particular task.

Command Syntax

show trace [*task_name*]

Syntax Description

Parameters	Description
<i>task_name</i>	The name of the task for which you want to display the trace information.

Usage Guidelines

If you do not enter any parameters, the command returns a list of available tasks.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

Example

This example displays trace information for CDP.

```
show trace cdps
```

show ups status

This command shows the current status of the USB-connected APC smart-UPS device and starts the monitoring service if not already started.

Command Syntax

show ups status

Usage Guidelines

This command only can provide a complete status on 7835-H2 and 7825-H2 servers.

show version

This command displays the software version on the active or inactive partition.

Command Syntax

show version {active|inactive}

Syntax Description

Parameters	Description
active	Displays the version running on the active partition.
inactive	Displays the version on the inactive partition.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show webapp session timeout

This command displays the webapp session timeout value, which is the amount of time, in minutes, that can elapse before a web application times out and logs off the user.

Command Syntax

show webapp session timeout

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

show web-security

This command displays the contents of the current web-security certificate.

Command Syntax**show web-security****Requirements**

Command privilege level: 0

Allowed during upgrade: Yes

show workingdir

This command retrieves the current working directory for activelog, inactivelog, install, and TFTP.

Command Syntax**show workingdir****Command Mode**

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

Unset Commands

unset ipsec

This command allows you to disable IPsec policies and associations.

Command Syntax

Command	Result
unset ipsec policy {ALL <i>policy-name</i> }	

Command	Result
unset ipsec association <i>policy-name</i> { ALL <i>association-name</i> }	

Syntax Description

Parameters	Description
<i>policy-name</i>	The name of an IPsec policy.
<i>association-name</i>	The name of an IPsec association.

Requirements

Command privilege level: 1

Allowed during upgrade: No

unset network

This command unsets DNS options.

Command Syntax

unset network dns options [**timeout**] [**attempts**] [**rotate**]

Syntax Description

Parameters	Description
timeout	Sets the wait time before the system considers a DNS query failed to the default.
attempts	Sets the number of DNS attempts to make before failing to the default.
rotate	Sets the method for selecting a name server to the default. This affects how loads are distributed across name servers.

Usage Guidelines

The system asks whether you want to continue to execute this command.



Caution

If you continue, the system temporarily loses network connectivity.

unset network domain

This command unsets the domain name and restarts the server.

Command Syntax

unset network domain

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

Utils Commands

utils auditd

This command starts, stops, and provides the status of the system auditing service.

Command Syntax

utils auditd {enable|disable|status}

Syntax Description

Parameters	Description
enable	Enables the collection of audit logs. When enabled, the system monitors and records user actions as well as Linux events such as the creation and removal of users, as well as the editing and deleting of files.
disable	Disables the collection of audit logs.
status	Displays the status of audit log collection. Cisco recommends that you retrieve the audit log by using the Real-Time Monitoring Tool, but you can also retrieve it by using the CLI.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

Useage Guidelines

After the service has been enabled, it monitors and logs activity on the system. Be aware that the system auditing service logs a lot of information. Care must be taken not to overfill the disk.

utils core list

This command lists all existing core files.

Command Syntax

`utils core {active|inactive} list`

utils core analyze

This command generates a backtrace for the specified core file, a thread list, and the current value of all CPU registers.

Command Syntax

`utils core analyze core file name`

Syntax Description

Parameters	Description
<i>core file name</i>	Specifies the name of a core file.

Usage Guidelines

The command creates a file of the same name as the core file, with a .txt extension, in the same directory as the core file. This command works only on the active partition.

utils create report

This command creates reports about the server in the platform or log directory.

Command Syntax

`utils create report {hardware|platform|csa}`

Syntax Description

Parameters	Description
hardware	Creates a system report containing disk array, remote console, diagnostic, and environmental data.
platform	Collects all of the platform configuration files into a TAR file.

Parameters	Description
csa	Collects all the files required for CSA diagnostics and assembles them into a single CSA diagnostics file. You can retrieve this file by using the file get command.

Usage Guidelines

You are prompted to continue after you enter the command.

After creating a report, to get the report use the command **file get activelog platform/log/filename**, where *filename* is the report filename that is displayed after the command completes.

Requirements

Level privilege: 1

Command privilege level: 0

Allowed during upgrade: Yes

utils create report database

Collects all log files needed for database troubleshooting.

Command Syntax

Utils create report database.

Example

```
admin:utils create report database
Created /var/log/active/cm/log/informix/[hostname]_db_report_Oct_27_11_13_10 for log
collection...
Collecting database logs, please be patient...
Collecting message logs (ccm.log) and assert failure files (af files)...
Collecting ris and ats files...
Collecting DB Replication logs...
Collecting DB install logs...
Collecting dblrpc and dbmon logs...
Collecting CDR information...
COMPLETED! Database report created successfully...
To retrieve the [hostname]_db_report_Oct_27_11_13_10.tar, use CLI command:
  file get activelog cm/log/informix/[hostname]_db_report_Oct_27_11_13_10.tar
To delete the [hostname]_db_report_Oct_27_11_13_10.tar, use CLI command:
  file delete activelog cm/log/informix/[hostname]_db_report_Oct_27_11_13_10.tar
```

utils dbreplication dropadmindb

This command drops the Informix syscdr database on any server in the cluster.

Command Syntax

utils dbreplication dropadmindb

Usage Guidelines

You should run this command only if database replication reset or cluster reset fails and replication cannot be restarted.

Command Modes

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: No

Applies to: Unified Communications Manager, IM and Presence service on Unified Communications Manager, Cisco Unity Connection.

utils dbreplication status

This command displays the status of database replication. Use this command only on the first publisher server of a cluster.

Command Syntax

utils dbreplication status

utils dbreplication stop

This command stops the automatic setup of database replication. Run this command on subscriber and publisher servers before executing the CLI command **utils dbreplication reset** or **utils dbreplication clusterreset**. You can run this command on the subscriber servers simultaneously, before you run it on the publisher server.

Command Syntax

utils dbreplication stop {*nodename*| **all**}

Syntax Description

Parameters	Description
<i>nodename</i>	Specifies the name of the node on which to stop the automatic setup of database replication.
all	Stops database replication on all nodes.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: No

utils dbreplication repair

This command repairs database replication.

Command Syntax

utils dbreplication repair

utils dbreplication reset

This command resets and restarts database replication.

Command Syntax

utils dbreplication reset

Usage Guidelines

You must restart the Emergency Responder Subscriber node from CUOS Administration or using the CLI command **utils system restart** after executing **utils dbreplication reset** command. See **help utils dbreplication reset** CLI command for more details.

utils diagnose

This command enables you to diagnose and attempt to automatically fix system problems.

Command Syntax

utils diagnose {**fix**|**list**|**module**|**test**|**version**} [*module_name*]

Syntax Description

Parameters	Description
fix	Runs all diagnostic commands and attempts to fix problems.
list	Lists all available diagnostic commands.
module	Runs a single diagnostic command or group of commands and attempts to fix problems.
test	Runs all diagnostic commands but does not attempt to fix problems.
version	Displays the diagnostic framework version.

Parameters	Description
<i>module_name</i>	The name of a diagnostics module.

utils diagnose test

This command enables you to run all diagnostic commands but does not attempt to fix any problems.

Command Syntax

```
utils diagnose test
```

utils disaster_recovery backup network

This command starts a backup job and stores the resulting tar file on a remote server.

Command Syntax

```
utils disaster_recovery backup network [featurelist] [path] [servername] [username]
```

Syntax Description

Parameters	Description
<i>featurelist</i>	Specifies the list of features to back up, separated by commas.
<i>path</i>	Represents the location of the backup files on the remote server.
<i>servername</i>	Represents the IP address or host name of the server where you stored the backup files.
<i>username</i>	Represents the username that is needed to log in to the remote server.

Usage Guidelines



Note

The system prompts you to enter the password for the account on the remote server.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils disaster_recovery cancel_backup

This command cancels the ongoing backup job.

Command Syntax

utils disaster_recovery cancel_backup

Usage Guidelines

The system prompts you to confirm that you want to cancel the backup job.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils disaster_recovery device add_network

This command adds the backup network device.

Command Syntax

utils disaster_recovery device add_network *device_name path server_name/ip_address username*
[*Number_of_backups*]

Syntax Description

Parameters	Description
<i>device_name</i>	The name of the backup device to be added.
<i>path</i>	The path to retrieve backup device from this location.
<i>server_name/ip_address</i>	The hostname or IP address of the server where the backup file needs to be stored.
<i>username</i>	the user ID to connect to remote machine
<i>Number_of_backups</i>	(Optional)The number of backups to store on Network Directory(default 2).

Example

Use the following example when running the utils disaster_recovery device add_network command:

```
utils disaster_recovery device add_network
networkDevice /root 10.77.31.116 root 3
```


Requirements

Command privilege level: 1
 Allowed during upgrade: No

utils disaster_recovery device delete

This command deletes the device.

Command Syntax

utils disaster_recovery device delete *device_name*|*

Syntax Description

Parameters	Description
<i>device_name</i>	The name of the device to be deleted.
*	Deletes all the existing devices except for the ones associated to a schedule.

Requirements

Command privilege level: 1
 Allowed during upgrade: No

utils disaster_recovery device list

This command shows the device name, device type, and device path for all the backup devices.

Command Syntax

utils disaster_recovery device list

Example

The following example shows how to run this command:

```
utils disaster_recovery device list
sftpdevice          NETWORK          10.77.31.116 : /root
tapedevice          TAPE             /dev/nst0
localdevice         LOCAL            /common/drftbackup
```

Requirements

Command privilege level: 1
 Allowed during upgrade: Yes

utils disaster_recovery estimate_tar_size

estimate_tar_size help:

This command provides the estimated size of last successful backup from SFTP/Local device.

Syntax Description

Parameters	Description
Name of the tar	This will give the tar file name through which the size can be estimated.

Example

```
admin:utils disaster_recovery estimate_tar_size CER
Estimated tar size successfully: Estimated size of backup for selected feature(s) is 42.52
MB.
```

utils disaster_recovery history

This command shows the history of a previous backup or restore

Command Syntax

utils disaster_recovery history *operation*

Syntax Description

Parameters	Description
<i>operation</i>	The name of an operation such as backup or restore.

Example

The following example shows how to run this command:

```
utils disaster_recovery history backup
Tar Filename: Backup Device: Completed On: Result: Backup Type: Features Backed Up:
2009-10-30-14-53-32.tar TAPE Fri Oct 30 14:55:31 CDT 2009 ERROR MANUAL
2009-12-10-10-30-17.tar TAPE Thu Dec 10 10:35:22 CST 2009 SUCCESS MANUAL
CDR_CAR,CCM
```

utils disaster_recovery jschLogs

This command enables and disables detailed JSch logging.

Example

```
drfCliCommand: JSch detailed logging enabled.
Restart DRS Master and Local Agent in this machine for the changes to take effect.
```

```
drfCliCommand: JSch detailed logging disabled.
Restart DRS Master and Local Agent in this machine for the changes to take effect.
JSch logs deleted successfully.
```

utils disaster_recovery schedule add

This command adds the configured schedules.

Command Syntax

```
utils disaster_recovery schedule add schedulename devicename featurelist datetime frequency
```

Syntax Description

Parameters	Description
<i>schedulename</i>	The name of the scheduler.
<i>devicename</i>	The name of the device for which scheduling is done.
<i>featurelist</i>	The comma-separated feature list to back up.
<i>datetime</i>	The date when the scheduler is set. The format is (yyyy/mm/dd-hh:mm) 24-hr clock.
<i>frequency</i>	The frequency at which the scheduler is set to receive a backup. For example: ONCE, DAILY, WEEKLY and MONTHLY .

Example

The following example show how to run this command:

```
utils disaster_recovery schedule add schedulename devicename featurelist
datetime frequency
Schedule has been saved successfully.
```

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils disaster_recovery schedule delete

This command deletes the specified schedule.

Command Syntax

```
utils disaster_recovery schedule delete schedulename*
```

Syntax Description

Parameters	Description
<i>schedulename</i>	The name of the schedule that needs to be deleted.
*	Deletes all of the existing schedules.

Example

The following example shows how this command is run:

```
utils disaster_recovery schedule delete schedule1|
Schedules deleted successfully.
```

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils disaster_recovery schedule disable

This command disables the specified schedule.

Command Syntax

```
utils disaster_recovery schedule disable schedulename
```

Syntax Description

Parameters	Description
<i>schedulename</i>	The name of the schedule that needs to be disabled.

Example

The following example shows how to run this command:

```
utils disaster_recovery schedule disable schedule1
Schedule disabled successfully.
```

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils disaster_recovery schedule enable

This command enables the specified schedule.

Command Syntax

utils disaster_recovery schedule enable *schedulename*

Syntax Description

Parameters	Description
<i>schedulename</i>	The name of the schedule that needs to be enabled.

Example

The following example shows how to run this command:

```
utils disaster_recovery schedule enable schedule1
Schedule enabled successfully.
```

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils disaster_recovery schedule list

This command displays all the of configured schedules.

Command Syntax

utils disaster_recovery schedule list

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils disaster_recovery restore network

This command starts a restore job and takes the backup tar file from a remote server.

Command Syntax

utils disaster_recovery restore network *restore_server tarfilename path servername username*

Syntax Description

Parameters	Description
<i>restore_server</i>	Specifies the hostname of the server that you want to restore.
<i>tarfilename</i>	Specifies the name of the file to restore.

Parameters	Description
<i>path</i>	Represents the location of the backup files on the remote server.
<i>servername</i>	Represents the IP address or host name of the server where you stored the backup files.
<i>username</i>	Represents the username that is needed to log in to the remote server.

Usage Guidelines



Note The system prompts you to enter the password for the account on the remote server.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils disaster_recovery show_backupfiles tape

This command displays information about the backup files that are stored on a tape.

Command Syntax

```
utils disaster_recovery show_backupfiles tape tapeid
```

Syntax Description

Parameters	Description
<i>tapeid</i>	Represents the ID of an available tape device.

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils disaster_recovery show_backupfiles network

This command displays information about the backup files that are stored on a remote server.

Command Syntax

utils disaster_recovery show_backupfiles network *path servername username*

Syntax Description

Parameters	Description
<i>path</i>	Represents the location of the backup files on the remote server.
<i>servername</i>	The IP address or host name of the server where you stored the backup files.
<i>username</i>	The username that is needed to log in to the remote server.

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils disaster_recovery show_registration

This command displays the registered features and components on the specified server.

Command Syntax

utils disaster_recovery show_registration *hostname*

Syntax Description

Parameters	Description
<i>hostname</i>	The server that you want to display registration information.

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils disaster_recovery status

This command displays the status of the current backup or restore job.

Command Syntax

utils disaster_recovery status *operation*

Syntax Description

Parameters	Description
<i>operation</i>	The name of the ongoing operation: backup or restore.

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils fior

This command allows you to monitor the I/O on the server.

Usage Guidelines

The file I/O reporting service provides a kernel-based daemon for collecting file I/O per process.

Command Syntax

Command	Result
utils fior	This command allows you to monitor the I/O on the server. The File I/O Reporting service provides a kernel-base daemon for collecting file I/O per process.
utils fior disable	
utils fior enable	
utils fior list [<i>start=date-time</i>] [<i>stop=date-time</i>]	This command displays a list of the I/O events for all processes.
utils fiorstart	
utils fior status	
utils fior stop	
utils fior top <i>number</i> [read write read-rate write-rate] [<i>start=date-time</i>] [<i>stop=date-time</i>]	This command displays a list of I/O statistics for I/O bound processes at the time that you run this command.

Syntax Description

Parameters	Description
disable	Prevents the file I/O reporting service from starting automatically when the machine boots. This command does not stop the service without a reboot. Use the stop option to stop the service immediately.
enable	Enables the file I/O reporting service to start automatically when the machine boots. This command does not start the service without a reboot. Use the start option to start the service immediately.
list	This command displays a list of file I/O events, in chronological order, from oldest to newest.
start	Starts a previously stopped file I/O reporting service. The service remains in a started state until it is manually stopped or the machine is rebooted.
status	Displays the status of the file I/O reporting service.
stop	Stops the file I/O reporting service. The service remains in a stopped state until it is manually started or the machine is rebooted.
top	Displays a list of top processes that create file I/O. This list can be sorted by the total number of bytes read, the total number of bytes written, the rate of bytes read, or the rate of bytes written.
start	Specifies a starting date and time.
stop	Specifies a stopping date and time.
<i>date-time</i>	Specifies a date and time, in any of the following formats: H:M, H:M:S a, H:M, a, H:M:S Y-m-d, H:M, Y-m-d, H:M:S.
<i>number</i>	Specifies how many of the top processes to list.
[read write read-rate write-rate]	Specifies the metric used to sort the list of the top processes.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils firewall

This command manages the firewall on the node.

Command Syntax

Command	Result
<code>utils firewall {enable disable[time]}</code>	This commands enables and disables firewall.
<code>utils firewall list</code>	This commands displays the current configuration of the firewall.
<code>utils firewall status</code>	This command displays the current status of the IPv4 firewall.

Syntax Description

Parameters	Description
<code>disable</code>	Disables the firewall.
<i>time</i>	The duration for which the firewall is disabled, in one of these formats: <ul style="list-style-type: none"> • [0–1440]m to specify a duration in minutes. • [0–24]h to specify a duration in hours. • [0–23]h[0–60]m to specify a duration in hours and minutes. • If you do not specify a time, the default is 5 minutes.
<code>list</code>	The current firewall configuration.
<code>status</code>	The status of the firewall.

Usage Guidelines

When the firewall is disabled, you must enter the URL of the Cisco Unified Communications Manager server in the following format to log into the web interface:

`https://server:8443/`

where *server* is the server name or IP address of the server.

Disabling the firewall is not recommended.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils firewall ipv4

This command enables and disables IPv4 firewall.

Command Syntax

```
utils firewall ipv4 {enable|disable}[time]}
```

Syntax Description

Parameters	Description
enable	Turns on the IPv4 firewall.
disable	Turns off the IPv4 firewall. If you do not enter the time parameter, this command disables the firewall for 5 minutes.
<i>[time]</i>	(Optional) Sets the duration for which the firewall is to be disabled in the following formats: <ul style="list-style-type: none"> • Minutes: 0–1440m • Hours: 0–23h • Hours and minutes: 0–23h 0–60m

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils firewall ipv4 debug

This command turns IPv4 firewall debugging on or off. If you do not enter a time parameter, this command turns on debugging for 5 minutes.

Command Syntax

```
utils firewall ipv4 debug {off} [time]}
```

Syntax Description

Parameters	Description
off	Enables the collection of audit logs. When enabled, the system monitors and records user actions as well as Linux events such as the creation and removal of users, as well as the editing and deleting of files.
<i>[time]</i>	(Optional) Disables the collection of audit logs.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils firewall ipv4 list

This command displays the current configuration of the IPv4 firewall.

Command Syntax

utils firewall ipv4 list

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils firewall ipv4 status

This command displays the current status of the IPv4 firewall.

Command Syntax

utils firewall ipv4 status

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils import config

This command imports all configuration settings found on the platformConfig.xml file and then reboots the system.

Command Syntax

utils import config

utils iostat

This command displays the iostat output for the given number of iterations and interval.

Command Syntax

utils iostat [*interval*] [*iterations*] [*filename*]

Syntax Description

Parameters	Description
<i>interval</i>	The value in seconds between two iostat readings (mandatory if you specify the number of iterations).
<i>iterations</i>	The number of iostat iterations to be performed (mandatory if you specify an interval).
<i>filename</i>	Redirects the output to a file.

Requirements

Level privilege: 0

Command privilege: 1

Allowed during upgrade: No

utils iothrottle enable

This command enables I/O throttling enhancements. When enabled, I/O throttling enhancements lower the impact of upgrades on an active system.

Command Syntax

```
utils iothrottle enable
```

utils iothrottle disable

This command disables I/O throttling enhancements.

Usage Guidelines

This could adversely affect the system during upgrades.

Command Syntax

```
utils iothrottle disable
```

utils iothrottle status

This command displays the status of I/O throttling enhancements.

Command Syntax

```
utils iothrottle status
```

utils network arp

This command lists, sets, or deletes Address Resolution Protocol (ARP) table entries.

Command Syntax

Command	Result
<code>utils network arplist [host <i>host</i>] [page] [numeric]</code>	This command lists the contents of the Address Resolution Protocol table.
<code>utils network arpset {<i>host</i>} {<i>address</i>}</code>	This command sets an entry in the Address Resolution Protocol table.
<code>utils network arpdelete <i>host</i></code>	This command deletes an entry in the Address Resolution Protocol table.

Syntax Description

Parameters	Description
<code>list</code>	Lists the contents of the address resolution protocol table.
<code>set</code>	sets an entry in the address resolution protocol table.

Parameters	Description
delete	deletes an entry in the address resolution table.
<i>host</i>	represents the host name or IP address of the host to add or delete to the table.
<i>address</i>	represents the MAC address of the host to be added. Enter the MAC address in the following format: XX:XX:XX:XX:XX:XX.
page	Displays the output one page at a time.
numeric	Displays hosts as dotted IP addresses.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils network capture eth0

This command captures IP packets on the specified Ethernet interface.

Command Syntax

```
utils network capture eth0 [page] [numeric] [file fname] [count num] [size bytes] [src addr] [dest addr]
[port num]
```

Syntax Description

Parameters	Description
eth0	Specifies Ethernet interface 0.
page	(Optional)Displays the output one page at a time. When you use the page or file options, the complete capture of all requested packets must occur before the command completes.
numeric	(Optional)Displays hosts as dotted IP addresses.
file <i>fname</i>	(Optional)Outputs the information to a file. The file option saves the information to platform/cli/ <i>fname</i> .cap. The filename cannot contain the "." character.
count <i>num</i>	(Optional)Sets a count of the number of packets to capture. For screen output, the maximum count equals 1000 and, for file output, the maximum count equals 10,000.

Parameters	Description
size bytes	(Optional)Sets the number of bytes of the packet to capture. For screen output, the maximum number of bytes equals 128, for file output, the maximum of bytes can be any number or ALL .
src addr	(Optional)Specifies the source address of the packet as a host name or IPV4 address.
dest addr	(Optional)Specifies the destination address of the packet as a host name or IPV4 address.
port num	(Optional)Specifies the port number of the packet, either source or destination.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils network connectivity

This command verifies the server's network connection to the publisher server. It is only valid on a subscriber server.

Command Syntax

utils network connectivity

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils network connectivity output

This command verifies the node network connection to the first node in the cluster. It is for Cisco Emergency Responder Subscriber only.

Command Syntax

utils network connectivity output

utils network host

This command resolves a host name to an address or an address to a host name.

Command Syntax

utils network host *hostname* [**server** *server-name*] [**page**] [**detail**] [**srv**]

Syntax Description

Parameters	Description
<i>hostname</i>	The host name or IP address that you want to resolve.
<i>server-name</i>	(Optional)Specifies an alternate domain name server.
page	(Optional)Displays the output one screen at a time.
detail	(Optional)Displays a detailed listing.
srv	(Optional)Displays DNS SRV records.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils network ping

This command allows you to ping another server.

Command Syntax

utils network ping *destination* [*count*]

Syntax Description

Parameters	Description
<i>destination</i>	The hostname or IP address of the server that you want to ping.
<i>count</i>	(Option)Specifies the number of times to ping the external server. The default count equals 4.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils network traceroute

This command traces IP packets that are sent to a remote destination.

Command Syntax

utils network traceroute *destination*

Syntax Description

Parameters	Description
<i>destination</i>	The hostname or IP address of the server to which you want to send a trace.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils ntp

This command displays the NTP status or configuration.

Command Syntax

utils ntp {*status* | *config*}

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils ntp restart

This command restarts the NTP service.

Command Syntax

utils ntp restart

Parameters

None

Requirements

Level privilege: 0

Command privilege: 0
 Allowed during upgrade: Yes

utils ntp server add

The command adds up to 5 specified NTP servers.

Usage Guidelines

norestart results in the NTP service not being restarted after adding the servers.



Note

If the *norestart* option is used, an explicit restart of the NTP service is required for the changes to take effect.

Command Syntax

```
utils ntp server add s1 [s2 s3 s4 s5] [norestart]
```

Usage Guidelines

Note the following:

- Mandatory parameter: at least one NTP server to add.
- Optional parameters: up to four more ntp servers and the norestart option.

Example

Adding servers with incorrect command line parameters

```
-----
admin:utils ntp server add s1 s2 s3 s4 s5 s6 s7 s8
Incorrect number of parameters entered for add
usage: utils ntp server add s1 [s2 s3 s4 s5] [norestart]
admin:
```

Example 2

Adding using norestart without specifying a server

```
-----
admin:utils ntp server add norestart
At least one NTP server must be specified for add operation.
usage: utils ntp server add s1 [s2 s3 s4 s5] [norestart]
```

Example 3

Adding servers without norestart

```
-----
admin:utils ntp server add clock1.cisco.com clock2.cisco.com
clock1.cisco.com : added successfully.
clock2.cisco.com : added successfully.
Restarting NTP on the server.
```

Example 4**Adding servers that are already added, without norestart**

```
-----
admin:utils ntp server add clock1.cisco.com clock2.cisco.com
clock1.cisco.com : [The host has already been added as an NTP server.]
clock2.cisco.com : [The host has already been added as an NTP server.]
admin:
```

Example 5**Adding server to self without norestart**

```
-----
admin:utils ntp server add bglr-ccm26
bglr-ccm26 : [This server cannot be added as an NTP server.]
admin:
```

Example 6**Adding inaccessible server without norestart**

```
-----
admin:utils ntp server add clock3.cisco.com
clock3.cisco.com : [ Inaccessible NTP server. Not added. ]
admin:
```

Example 7**Adding servers with norestart**

```
-----
admin:utils ntp server add ntp01-syd.cisco.com ntp02-syd.cisco.com clock.cisco.com
norestart
ntp01-syd.cisco.com: added successfully.
ntp02-syd.cisco.com: added successfully.
clock.cisco.com: added successfully.
The NTP service must be restarted for the changes to take effect.
```

Example 8**Adding servers when 5 are already configured**

```
-----
admin:utils ntp server add clock3.cisco.com
The maximum permissible limit of 5 NTP servers is already configured
```

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils ntp server delete

The command deletes any configured NTP server or all of them.

Usage Guidelines

After the user enters their choice, they are prompted if they would like to restart the NTP service.

Answering No results in the NTP service not being restarted after deleting the servers.

**Note**

If the user chooses not to restart the NTP service, an explicit restart of the NTP service is required for the changes to take effect.

Command Syntax

```
utils ntp server delete
```

Example 1**Deleting servers with incorrect command line parameters**

```
-----
admin:utils ntp server delete clock1.cisco.com clock2.cisco.com
Incorrect number of optional parameters entered for delete
usage: utils ntp server delete
admin:
```

Example 2**Deleting single server with ntp restart**

```
-----
admin:utils ntp server delete
1: clock1.cisco.com
2: clock2.cisco.com
3: ntp01-syd.cisco.com
4: ntp02-syd.cisco.com
5: clock.cisco.com
a: all
q: quit
Choice: 1
Restart NTP (y/n): y
clock1.cisco.com is deleted from the list of configured NTP servers.
Continue (y/n)?y
clock1.cisco.com: deleted successfully.
Restarting NTP on the server.
admin:
```

Example 3**Deleting all servers without ntp restart**

```
-----
admin:utils ntp server delete
1: clock1.cisco.com
2: clock2.cisco.com
3: ntp01-syd.cisco.com
4: ntp02-syd.cisco.com
5: clock.cisco.com
a: all
q: quit
Choice: a
Restart NTP (y/n): n
This results in all the configured NTP servers being deleted.
Continue (y/n)?y
clock1.cisco.com: deleted successfully.
clock2.cisco.com: deleted successfully.
ntp01-syd.cisco.com: deleted successfully.
ntp02-syd.cisco.com: deleted successfully.
clock.cisco.com: deleted successfully.
The NTP service must be restarted for the changes to take effect.
admin:
```

Example 4**Deleting all servers when no servers are configured**

```
-----  
admin:utils ntp server delete  
There are no NTP servers configured to delete.
```

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils ntp server list

The command lists the configured NTP servers.

Command Syntax

utils ntp server list

Example 1**Listing servers with incorrect command line parameters**

```
-----  
admin:utils ntp server list all  
Incorrect optional parameter entered for list  
usage: utils ntp server list  
admin:
```

Example 2**Listing servers**

```
-----  
admin:utils ntp server list  
clock1.cisco.com  
clock2.cisco.com  
ntp01-syd.cisco.com  
ntp02-syd.cisco.com  
clock.cisco.com  
admin:
```

Example 3**Listing servers when no servers are configured**

```
-----  
admin:utils ntp server list  
There are no NTP servers configured.
```

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils ntp start

This command starts the NTP service, if it is not already running.

**Note**

You cannot stop the NTP service from the CLI. Use this command when the **utils ntp status** command returns **stopped**.

Command Syntax

utils ntp start

Requirements

Level privilege: 0

Command privilege: 0

Allowed during upgrade: Yes

utils os kerneldump

This command configures kerneldump to provide a kernel crash dumping mechanism. The kernel captures the dump to the local disk, in case of a kernel crash.

**Note**

The netdump commands have been removed from release 8.6(1) and have been replaced with the kerneldump commands.

Command Syntax

utils os kerneldump {enable|disable}

Usage Guidelines

If a kernel crash occurs, the capture kernel dumps the core on the local disk of the server. The primary kernel reserves 128MB of physical memory that the capture kernel uses to boot. The kerneldump uses the **kexec** command to boot into a capture kernel whenever the kernel crashes.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

Example

```
admin: utils os kerneldump enable
*****WARNING*****
Enabling kerneldump requires system reboot
Would you like to boot the machine (y/n):y
```

```
kerneldump enable operation succeeded
System going for a reboot
```

utils os kerneldump ssh

This command enables, disables, or displays the status of an external SSH server.

Command Syntax

```
utils os kerneldump ssh {enable|disable|status}
```

Syntax Description

Parameters	Description
enable	Configures an external SSH server as a kerneldump server to collect kernel dumps.
disable	Removes support of the external SSH server that is configured to collect kernel dumps.
status	Indicates whether an external SSH server is configured or not, to collect kernel dumps.

Usage Guidelines

If external SSH server has the kerneldump service enabled and a kernel crash occurs, the capture kernel dumps the core on the external server that is configured to collect the dump. Enabling and disabling kerneldump require a system reboot for the changes to come into effect.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

Example

```
admin: utils os kerneldump ssh disable 10.77.31.60
Disabling kerneldump requires system reboot
Would you like to continue (y/n): y
kerneldump disable operation succeeded
System going for a reboot
```

utils os secure

This command is used to specify the level of security provided by selinux.

Command Syntax

utils os secure {enforce |permissive|status}

Usage Guidelines

The selinux does not handle rate limiting. Rate limiting is handled by ipprefs and ip tables.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils remote_account

This command allows you to enable, disable, create, and check the status of a remote account.

Command Syntax

Command	Result
utils remote_account status	This command allows you to check the status of a remote account.
utils remote_account enable	This command allows you to enable a remote account.
utils remote_account disable	This command allows you to disable a remote account.
utils remote_account create <i>username life</i>	This command creates a remote account.

Syntax Description

Parameters	Description
<i>username</i>	The name of the remote account. The username can contain only lowercase characters and must be more than six-characters long.
<i>life</i>	The life of the account in days. After the specified number of day, the account expires.

Usage Guidelines

A remote account generates a pass phrase that allows Cisco Systems support personnel to get access to the system for the specified life of the account. You can have only one remote account that is enabled at a time.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

Example

```
utils remote_account status
```

utils reset_application_ui_administrator_name

This command resets the application user interface administrator name.

Command Syntax

```
utils reset_application_ui_administrator_name
```

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils reset_application_ui_administrator_password

This command resets the application user interface administrator password.

Command Syntax

```
utils reset_application_ui_administrator_password
```

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils service

This command stops, starts, or restarts a service.

Command Syntax

```
utils service {start|stop|restart|auto-restart {enable|disable|show}} service-name
```

Syntax Description

Parameters	Description
<i>service-name</i>	The name of the service that you want to stop or start: <ul style="list-style-type: none"> • System NTP • System SSH • Cisco IDS • Cisco Tomcat • Cisco Database Layer Monitor • Cisco Emergency Responder • Cisco Phone Tracking Engine
auto-restart	Causes a service to automatically restart.
enable	Enables auto-restart
disable	Disables auto-restart.
show	Shows the auto-restart status.

Requirements

Command privilege level: 1
Allowed during upgrade: No

utils service list

This command retrieves a list of all services and their status.

Command Syntax

utils service list [**page**]

Syntax Description

Parameters	Description
page	(Option)Displays the output one page at a time.

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils snmp

This command manages SNMP on the server.

Command Syntax

utils snmp get <i>version community ip-address object [file]</i>	This interactive command gets the SNMP data using the specified version for the specified MIB OID.
utils snmp hardware-agents [status restart]	This command affects the SNMP agents on the server.
utils snmp test	
utils snmp walk <i>version community ip-address object [file]</i>	This interactive commands walks through the SNMP MIB.

Syntax Description

Parameters	Description
get	Displays the value of the specified SNMP object.
hardware-agents status	Displays the status of the hardware agents on the server.
hardware-agents	Stops all SNMP agents provided by the hardware vendor.
hardware-agents restart	Restarts the hardware agents on the server.
test	Tests the SNMP host by sending sample alarms to local syslog and remote syslog.
walk	Walks the SNMP MIB, starting with the specified SNMP object.
<i>version</i>	Specifies the SNMP version. Possible values are 1 or 2c.
<i>community</i>	Specifies the SNMP community string.
<i>ip-address</i>	Specifies the IP address of the server. Enter 127.0.0.1 to specify the local host. You can enter the IP address of another node in the cluster to run the command on that node.
<i>object</i>	Specifies the SNMP Object ID (OID) to get.
<i>file</i>	Specifies a file in which to save the command output.

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils snmp config 1/2c community-string

This interactive command adds, deletes, lists or updates a community string.

Command Syntax

utils snmp config 1/2c community-string {add|delete|list|update}

Syntax Description

Parameters	Description
add	Adds a new community string.
delete	Deletes a community string.
list	Lists all community strings.
update	Updates a community string.

Useage Guidelines

The system prompts you for the parameters.

The SNMP Master Agent service is restarted for configuration changes to take effect. Do not abort command after execution until restart is complete. If the command is aborted during service restart, verify service status of SNMP Master Agent by using **utils service list**. If service is down, start it by using **utils service start SNMP Master Agent** .

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils snmp config 3 user

This interactive command affects v3 user configuration.

Command Syntax

utils snmp config 3 user {add|delete|list|update}

Syntax Description

Parameters	Description
add	Adds a new v3 user with the v3 authentication and privacy passwords.
delete	Deletes the configuration information for an existing v3 user.
list	Lists the v3 users currently configured.
update	Updates configuration information for an existing v3 user.

Usage Guidelines

The system prompts you for the parameters.

Command Mode

Administrator (admin:)

Requirements

Command privilege level:1

Allowed during upgrade: Yes

utils snmp config mib2

This command affects the Mib2 configuration information.

Command Syntax

utils snmp config mib2 {add|delete|list|update}

Syntax Description

Parameters	Description
add	Adds the Mib2 configuration information.
delete	Deletes the Mib2 configuration information.
list	Lists the Mib2 configuration information.
update	Updates the Mib2 configuration information.

Usage Guidelines

The system prompts you for the parameters.

Command Mode

Administrator (admin:)

Requirements

Command privilege level: 1

Allowed during upgrade: Yes

utils snmp walk 3

This command is used to walk the SNMP MIB starting with the specified OID.

Command Syntax**utils snmp walk 3**

[system prompts you for the parameters]

Example

If you run `snmp walk` on a leaf in the MIB you basically get what you would get with '`utils snmp get ...`' command. Here is the sample walk output we are getting for the OID 1.3.6

```
iso.3.6.1.2.1.1.1.0 = STRING: "Hardware:7825H, 1 Intel(R) Pentium(R) 4 CPU
3.40GHz, 2048 MB Memory: Software:UCOS 2.0.1.0-62"
iso.3.6.1.2.1.1.2.0 = OID: iso.3.6.1.4.1.9.1.583
iso.3.6.1.2.1.1.3.0 = Timeticks: (15878339) 1 day, 20:06:23.39
iso.3.6.1.2.1.1.4.0 = ""
iso.3.6.1.2.1.1.5.0 = STRING: "bldr-ccm34.cisco.com"
iso.3.6.1.2.1.1.6.0 = ""
iso.3.6.1.2.1.1.7.0 = INTEGER: 72
iso.3.6.1.2.1.2.1.0 = INTEGER: 3
iso.3.6.1.2.1.2.2.1.1.1 = INTEGER: 1
iso.3.6.1.2.1.2.2.1.1.2 = INTEGER: 2
iso.3.6.1.2.1.2.2.1.1.3 = INTEGER: 3
iso.3.6.1.2.1.2.2.1.2.1 = STRING: "lo"
iso.3.6.1.2.1.2.2.1.2.2 = STRING: "eth0"
iso.3.6.1.2.1.2.2.1.2.3 = STRING: "eth1"
iso.3.6.1.2.1.2.2.1.3.1 = INTEGER: 24
iso.3.6.1.2.1.2.2.1.3.2 = INTEGER: 6
iso.3.6.1.2.1.2.2.1.3.3 = INTEGER: 6
iso.3.6.1.2.1.2.2.1.4.1 = INTEGER: 16436
iso.3.6.1.2.1.2.2.1.4.2 = INTEGER: 1500
iso.3.6.1.2.1.2.2.1.4.3 = INTEGER: 1500
iso.3.6.1.2.1.2.2.1.5.1 = Gauge32: 0
iso.3.6.1.2.1.2.2.1.5.2 = Gauge32: 100000000
iso.3.6.1.2.1.2.2.1.5.3 = Gauge32: 100000000
iso.3.6.1.2.1.2.2.1.6.1 = Hex-STRING: 00 00 00 00 00 00 00
iso.3.6.1.2.1.2.2.1.6.2 = Hex-STRING: 00 16 35 5C 61 D0
iso.3.6.1.2.1.2.2.1.6.3 = Hex-STRING: 00 16 35 5C 61 CF
iso.3.6.1.2.1.2.2.1.7.1 = INTEGER: 1
.....
```

If you provide an IP address of a remote host the command is executed on that remote host. You have to provide the IP address, not the domain name.

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils snmp get 3

This command gets the SNMP data for the specified MIB OID.

Command Syntax

utils snmp get 3

[system prompts you for the parameters]

Usage Guidelines

If you use this command on a specific OID (leaf) in the MIB, you will get the value of the MIB. The SNMP get output of system uptime iso.3.6.1.2.1.25.1.1.0 = Timeticks: (19836825) 2 days, 7:06:08.25

If you provide an IP address of a remote host, the command is executed on that remote host. You have to provide the IP address not the domain name.

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils system

This command restarts the system on the same partition, restarts the system on the inactive partition, or shuts down the system.

Command Syntax

utils system {restart | shutdown | switch-version}

Syntax Description

Parameters	Description
restart	Restarts the system.
shutdown	Shuts down the system.
switch-version	Switches to the product release installed on the inactive partition.

Usage Guidelines

The **utils system shutdown** command has a 5-minute timeout. If the system does not shut down within 5 minutes, the command gives you the option of doing a forced shutdown.

Requirements

Command privilege level: 1

Allowed during upgrade: No

utils system boot

This command redirects where the system boot output gets sent.

Command Syntax

utils system boot {console| serial| status}

Syntax Description

Parameters	Description
console	Redirects the system boot output to the console.
serial	Redirects the system boot output to the COM1 (serial port 1).
status	Displays the where the serial boot output currently gets sent.

Requirements

Level privilege: 1

Command privilege: 1

Allowed during upgrade: Yes

utils system upgrade

This command allows you to install upgrades and Cisco Option Package (COP) files from both local and remote directories.

Command Syntax

utils system upgrade {initiate | cancel | status}

Syntax Description

Parameters	Description
cancel	Cancels the active upgrade.
initiate	Starts a new upgrade wizard or assumes control of an existing upgrade wizard. The wizard prompts you for the location of the upgrade file.
status	Displays the status of an upgrade.

Usage Guidelines

To upgrade the system, follow these steps:

- 1 Use the **utils system upgrade list** command to display a list of the .iso upgrade files that are available on the local disk or remote server from which you plan to upgrade.
- 2 Use the **utils system upgrade get** command to get the upgrade file that you want to use.
- 3 Use the **utils system upgrade start** command to start upgrading from the upgrade file that you received.

utils vmtools status

This command shows the version of the currently running VMware Tools.

Command Syntax

utils vmtools status

Requirements

Command privilege level: 0

Allowed during upgrade: Yes

utils vmtools upgrade

This command updates the currently installed VMware Tools to the latest version required by the ESXi host for that VM.

Command Syntax

utils vmtools upgrade



INDEX

C

- Cisco Emergency Responder [5](#)
 - CLI [5](#)
- cli [5](#)
- CLI [1, 2, 3, 5](#)
 - completing commands [2](#)
 - ending a CLI session [3](#)
 - getting help [3](#)
 - starting a CLI session [1](#)
- clisessionstart [1](#)

D

- delete account command [5](#)
- delete dns command [6](#)
- delete ipsec command [7](#)
- delete process command [7](#)
- delete smtp command [8](#)

F

- file check command [8](#)
- file delete command [9](#)
- file dump command [10](#)
- file get command [11](#)
- file list command [12](#)
- file search command [13](#)
- file tail command [14](#)
- file view command [15](#)

R

- run sql command [16](#)

S

- set account command [16](#)
- set cli pagination command [21](#)
- set commandcount command [22](#)
- set ipsec command [26](#)
- set logging command [26](#)
- set network dhcp command [28](#)
- set network dns command [29](#)
- set network dns options command [29](#)
- set network domain command [30](#)
- set network failover command [30](#)
- set network gateway command [31](#)
- set network ip command [33](#)
- set network max_ip_contract command [34](#)
- set network mtu command [34](#)
- set network nic command [35](#)
- set network pmtud command [36](#)
- set network restore command [37](#)
- set network status command [37](#)
- set password command [38](#)
- set smtp command [46](#)
- set timezone command [47](#)
- set trace command [47](#)
- set web-security command [48](#)
- set workingdir command [50](#)
- show account command [50](#)
- show cert command [51](#)
- show cli pagination command [51](#)
- show ctl command [53](#)
- show diskusage command [53](#)
- show environment command [56](#)
- show hardware command [56](#)
- show logins command [58](#)
- show memory commands [58](#)
- show myself command [59](#)
- show network ipprefs command [61](#)
- show open command [62](#)
- show packages command [63](#)
- show process command [65](#)
- show smtp command [67](#)
- show stats io command [68](#)

show status command 68
show tech all command 69
show tech database command 69
show tech dbintegrity command 70
show tech dbinuse command 70
show tech dbschema command 71
show tech dbstateinfo command 71
show tech network command 71
show tech prefs command 72
show tech runtime command 73
show tech systables command 73
show tech system command 74
show tech table command 74
show tech version command 75
show timezone command 75
show trace command 76
show ups status command 77
show version command 77
show web-security command 78

U

unset ipsec command 78
unset network command 79
utils core analyze command 81
utils create report command 81
utils dbreplication repair command 84
utils dbreplication reset command 84
utils dbreplication status command 83
utils diagnose command 84
utils diagnose test command 85
utils disaster_recovery backup network command 85
utils disaster_recovery cancel_backup command 86
utils disaster_recovery restore network command 91
utils disaster_recovery show_backupfiles network command 92
utils disaster_recovery show_backupfiles tape command 92
utils disaster_recovery show_registration command 93
utils disaster_recovery status command 93
utils fior command 94
utils firewall command 96
utils iostat command 99
utils iothrottle disable command 100
utils iothrottle enable command 99
utils iothrottle status command 100
utils network arp command 100
utils network capture eth0 command 101
utils network connectivity command 102
utils network host command 102
utils network ping command 103
utils ntp command 104
utils ntp restart command 104
utils ntp start command 109
utils remote_account command 111
utils reset_application_ui_administrator_name command 112
utils reset_application_ui_administrator_password command 112
utils service command 112
utils service list command 113
utils snmp command 114
utils system boot command 119
utils system command 118
utils system upgrade command 119