Cisco Unified Attendant Console Standard Quick Reference Guide

This sheet gives a quick overview of how to use the Cisco Unified Attendant Console Standard interface. For full details, see the application help.

Starting Cisco Unified Attendant Console Standard

To start Cisco Unified Attendant Console Standard:

- 1 Double-click the desktop icon.
- 2 If required, enter an operator extension number.
- 3 If you want Cisco Unified Attendant Console Standard to remember the operator extension number to use automatically next time it is started, select **Remember Extension**.
- 4 Click Sign In.

To sign out from your current attendant console session, in the main menu, click **Sign Out**. The application continues to run and any synchronization currently in progress continues. To resume using the application, repeat step 2 to step 4.

Opening the Online Help

To open the application Help, press **F1**.

Line States and Directory Presence Status

The phone line state icons appear in the Call Control and Directory panes and represent the state of operator and extensions. The presence status icons are displayed in directories.

Operator Line State				
lcon	State			
	On hook			
9	Off hook			
0	Do not disturb			
×	Forwarded			
3	Out of service			

Participant Line State		
lcon	State	
***	Ringing	
3	Off hook	
11	On hold	

Directory Line State			
lcon	State		
**	Ringing		
	On hook		
3	Off hook		
\oslash	Do not disturb		
~	Forwarded		
9	Forwarded to voicemail		

Directory Presence Status		
lcon	Status	
•	Available	
•	Away, invisible or on the phone	
•	Do not disturb	
0	Unknown or off-line	

Cisco Unified Attendant Console Standard Quick Reference Guide

Using the Mouse to Apply Commonly Used Call Controls

This section describes how to make and control calls using the mouse. There are sometimes several ways of doing these things; the easiest or quickest is described here. You can also use the main menu or keyboard shortcuts for many actions. For detailed instructions on all the methods of call control, see the application Help.

То	Do this with the mouse	Main menu	Default keyboard shortcut
Make a call	In the Directory pane, double-click the contact.	✓	Ctrl+D
End a call	In the active call, click End.	✓	Ctrl+H
Answer a call	In the active call, click Answer .	✓	Ctrl+A
Hold a call	In the active call, click .	✓	Ctrl+L
Resume a call	In the active call, click Resume .	✓	★ (programmable)
Park a call	Drag the call from the Call Control pane to the Parked Calls pane.	✓	Ctrl+P
Retrieve a parked call	Drag the call from the Parked Calls pane to the Call Control pane.	×	* (programmable)
Divert a call	In the Call Control pane:	×	×
	1 In the ringing call, click Divert .		
	2 In the Dialpad search box, type the contact's name or number.		
	3 In the list, select the contact, and then click Divert .		
Enable call	In the Call Control pane:	×	×
forwarding	1 Right-click the operator extension, and then select Enable FWD .		
	2 In the Dialpad, search box, type the name or number to forward calls to, and then click Forward .		
Disable call forwarding	In the Call Control pane, right-click the operator extension, and then select Disable FWD .	×	×
Enable Do Not Disturb	In the Call Control pane, right-click the operator extension, and then select Enable DND .	×	×
Disable Do Not Disturb	In the Call Control pane, right-click the operator extension, and then select Disable DND .	×	×
Consult transfer a call	In the Call Control pane:	~	Ctrl+T
	1 Right-click the call and select Consult Transfer.		
	2 In the Dialpad search box, type the recipient contact's name or number.		
	3 In the list, select the recipient, and then click Consult .		
	4 When the recipient has answered and agreed to accept the call, in the Dialpad, click Transfer .		
	In the Directory:		
	1 In the directory search box, type the recipient contact's name or number.		
	2 In the directory, right-click the contact and select Consult Transfer.		
	The contact answers the call.		
	3 If the contact agrees to accept the call, perform a direct transfer (described below).		



Cisco Unified Attendant Console Standard Quick Reference Guide

То	Do this with the mouse	Main menu	Default keyboard shortcut
Blind transfer a call	Drag the call from the Call Control pane to the Directory pane, and then drop it on the recipient contact.	✓	Ctrl+X
	Alternatively:		
	1 In the active call, click the transfer icon .		
	2 In the Dialpad search box, type the recipient contact's name or number.		
	3 In the list, select the recipient, and then click Transfer .		
Direct transferring a	In the Call Control pane:	✓	Ctrl+R
call	1 Select one call, hold the Ctrl key and then select the other call.		
	2 Right-click and select Direct Transfer .		
Conferencing calls	In the Call Control pane:	✓	Ctrl+N
	1 Right-click the active call and select Conference.		
	2 In the Dialpad search box, type the name or number of a participant to include in the conference, and then click Dial .		
	3 When the participant answers, in the Dialpad, click Conference . The participant is added to the conference call.		
	4 For each additional participant, repeat 2. and 3.		
Joining calls	In the Call Control pane:	✓	Ctrl+J
	1 With one call selected, hold the Ctrl key and then select the other calls to join together.		
	2 Right-click the call and select Join .		
Transfer a call to	In the Call Control pane:	✓	Ctrl+O
voicemail	1 Right-click the active call and select Voicemail.		
	2 In the Dialpad search box, type the contact's number.		
	3 Select the contact, and then click Transfer .		
Email a contact	In the Call Control pane:	×	* (programmable)
	1 Right-click the active call, and then choose Email .		
	2 Use your e-mail system to complete and send the email.		
	To email a contact in a directory:		
	1 Right-click the contact, and then choose Email.		
	2 Use your e-mail system to complete and send the email.		